


TA8194Z

MUTING IC

The TA8194Z is a muting IC to prevent the "POP" noise made at time of power ON and OFF of audio equipments. This IC has 4 sensor terminals, muting control terminal and supply control terminal. In case of sensing voltage rising, muting control signal occurs and after that supply control signal occurs and muting signal maintains for 1s. In case of sensing voltage setting, muting control signal occurs and after that supply control signal stops. This IC also has manual muting terminal and protection function.



Weight : 0.99g (Typ.)


FEATURES

- 4 sensor terminals : V_{CC} , B_1 , B_2 , B_3
- Muting circuit control signal output
- Power supply circuit control signal output
- Manual muting control terminal
- Protection function terminal
- Operating supply voltage range : $V_{CC}(\text{opr.}) = 8 \sim 18.0\text{V}$ ($T_a = 25^\circ\text{C}$)

961001EBA1

- TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.
- The products described in this document are subject to foreign exchange and foreign trade control laws.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.

BLOCK DIAGRAM



TERMINAL EXPLANATION

PIN No.	FUNCTION	EQUIVALENT CIRCUIT
3	MUTE OUT	
	Muting Control Signal Output	
4	V _S OUT	
	Supply Control Signal Output	
5	TC (Timing Condenser)	
	Muting Time Condenser Terminal	
6	M. MUTE (Manual Mute)	
	$V_6 \geq 0.8V \rightarrow \text{MUTE OUT} = \text{ON}$	
7	V _{REF} (Reference Voltage)	
	Reference Voltage for Comparator	

PIN No.	FUNCTION	EQUIVALENT CIRCUIT
9	PROT. (Protection)	
	$V_9 \geq 0.8V \rightarrow \text{MUTE OUT} = \text{ON},$ $V_S \text{ OUT} = \text{OFF}$	
10	B3 Voltage Sense Terminal-3	
11	B2 Voltage Sense Terminal-2	
12	B1 Voltage Sense Terminal-1	
13	VCC	
	Supply Terminal Voltage Sense Terminal	
14	CH (Charge Hold)	
	Back Up Capacitor Terminal at VCC OFF	

OPERATING DESCRIPTION

The TA8194Z is a muting control IC to prevent pop noise made at time of power ON and OFF of audio equipments.

This IC has built-in 4 terminals for sensing bias line voltage of audio equipment.

According to sensing voltage rising and setting, this IC occurs muting control signal and supply control signal.




Followings are basic operation of this IC, refer to TIMING CHART : page 6.

- (1) Muting control signal occurs at V_{CC} ON under any condition of B1, B2, B3 sensing voltage.
- (2) Muting control signal occurs at V_S output OFF.
- (3) Muting control signal stops after (T_M ON) s at V_S output ON.
Muting time (T_M ON) depends on capacitor value connected to TC terminal : pin⑤.
(T_M ON) is 1.0~1.1s (Typ.) under condition of $C_{TC} = 10\mu F$.
The above are applied in case sensing voltage rises fast enough.
Muting control OFF sense voltage : (V_M OFF) is higher than V_S ON sense voltage (V_{VS} ON), so in case sensing voltage rises slowly, the period sensing voltage rising from (V_{VS} ON) to (V_M ON) should be counted.
- (4) Muting control signal occurs at V_{CC} OFF. In this case, muting time depends on capacitor value connected to CH terminal : Pin⑭. This capacitor is back-up capacitor at V_{CC} OFF. Muting control signal operation at V_{CC} OFF is by charge of this capacitor.
- (5) Manual muting control terminal : pin⑥.
Muting control signal occurs by adding H-level signal at manual mute control terminal under any condition of V_S control output.
- (6) V_S control output signal occurs at condition of sensing terminal voltage is following.
$$V_{CC} \cdot B1 \cdot (B2 + B3) = \text{H-level}$$
- (7) Sense voltage of V_S ON/OFF and muting ON/OFF control are set individually, so control signal output operate sequentially as follows.
 - Sensing voltage rising : V_S control output signal stop after muting control signal occurs.
(V_M ON > V_{VS} OFF)
 - Sensing voltage setting : Muting control signal stops after (T_M ON) s at sensing voltage setting to (V_M OFF) after V_S control output occurs. (V_{VS} ON < V_M OFF)

There are muting period before and after at V_S control signal stops and occurs.
- (8) Sense voltage of V_S ON/OFF and muting ON/OFF control have hysteresis voltage of 0.2~0.3V.
- (9) Protection function terminal : pin⑨.
 - Adding H-level control signal : V_S control signal stops and Muting control signal occurs.
 - Adding L-level control signal from H-level : V_S control signal occurs and after the period : DTp OFF, muting control signal stops.

DTp OFF depends on capacitor value connected to TC terminal as T_M ON.

TIMING CHART




MAXIMUM RATINGS (Ta = 25°C)







CHARACTERISTIC	SYMBOL	RATING	UNIT
Supply Voltage	VCC	25	V
Power Dissipation	PD	750	mW
Operating Temperature	Topr	- 30~85	°C
Storage Temperature	Tstg	- 55~150	°C



ELECTRICAL CHARACTERISTICS (Unless otherwise specified, $V_{CC} = 14.4V$, $V_{REF} = 6.8V$, $T_a = 25^{\circ}C$)

CHARACTERISTIC	SYMBOL	TEST CIR- CUIT	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Quiescent Current	I_{CCQ}	—	—	—	19	40	mA
Reference Current	I_{REF}	—	—	7.3	9.5	13.5	mA
Mute On Sense Voltage	$V_{M\ ON\ (1)}$	—	V_{CC} , B2, B3	8.5	8.7	8.9	V
	$V_{M\ ON\ (2)}$	—	B1	7.75	8.0	8.25	
Mute Off Sense Voltage	$V_{M\ OFF\ (1)}$	—	V_{CC} , B2, B3	—	9.0	9.2	V
	$V_{M\ OFF\ (2)}$	—	B1	—	8.2	9.2	
Mute Out Saturation Voltage	$V_{OUT\ ML}$	—	$I_{M\ OUT} = 10mA$	—	1.9	2.5	V
Mute On Dearly Time	$DT_{M\ ON}$	—	—	—	—	10	μs
V_S On Mute Time	$T_{M\ ON\ (1)}$	—	B1 or B2 or B3→ON	0.7	1.0	1.4	s
	$T_{M\ ON\ (2)}$	—	V_{CC} →ON	0.8	1.1	1.5	
V_S On Sense Voltage	$V_{VS\ ON\ (1)}$	—	V_{CC}	—	7.4	8.1	V
	$V_{VS\ ON\ (2)}$	—	B1, B2, B3	—	7.3	8.1	
V_S Off Sense Voltage	$V_{VS\ OFF}$	—	V_{CC} , B1, B2 B3	7.3	7.6	8.0	V
V_S Out Voltage	$V_{OUT\ VS}$	—	$I_{VS} = -20mA$	—	0.25	1.0	V
V_S Off Dearly Time	$DT_{VS\ OFF}$	—	—	—	—	10	μs
Protector On Trigger Voltage	$V_P\ ON$	—	—	0.8	—	—	V
Protector On Trigger Time	$T_P\ ON$	—	$V_P = 14.4V$	10	—	—	μs
Protector On Dearly Time	$DT_P\ ON$	—	$V_P = 14.4V$	—	—	10	μs
Protector On Input Current	$I_P\ IN$	—	$V_P\ IN = 1V$	—	—	0.1	mA
Protector Off Delay Time	$DT_P\ OFF$	—	—	0.7	—	1.5	s
Manual Mute On Sense Voltage	$V_{MM\ ON}$	—	—	0.8	—	—	V
Manual Mute On Dearly Time	$DT_{MM\ ON}$	—	$V_{MM} = 13.4V$	—	—	10	μs
Manual Mute On Input Current	$I_{MM\ IN}$	—	$V_{MM\ IN} = 1V$	—	—	0.1	mA

TEST CIRCUIT








OUTLINE DRAWING
ZIP16-P-1.27

Unit : mm



Weight : 0.99g (Typ.)