



## Earth Leakage Current Detector VG54123

The VG54123 is a semiconductor integrated circuit with amplifier for a high-speed earth leakage circuit breaker

### FEATURES

- ◆ Wide temperature range ( $T_a = -20^{\circ}\text{C} \sim +80^{\circ}\text{C}$ )
- ◆ Good temperature characteristics of input sensitivity current
- ◆ High input sensitivity ( $V_I = 6.1\text{mV Typ.}$ )
- ◆ Low external component count
- ◆ High noise and surge-proof
- ◆ Low power dissipation ( $P_d = 5\text{mW Typ.}$ ) and may be used both as 110V and 220V
- ◆ Sip8,Sop8 or Dip8 Package



### FUNCTION

The VG54123 circuit for the amplifying parts of earth leakage circuit breaker consists of differential amplifier,latch circuit and voltage regulator. It is connected to the secondary side of the zero current transformer (ZCT) which detects leakage current in the both input of the differential amplifier. Signals amplified by differential amplifier are integrated by an external capacitor, and connects to the input terminal of latch circuit with output suitable for the characteristics of high-speed earth leakage circuit breaker. Latch circuit keeps low in the output till the input voltage reaches the fixed level ,and output becomes high when the leakage current more than fixed flows. It drives a thyristor connected to the output terminal of latch circuit.

### PIN FUNCTIONS

PIN	Symbol	Function	PIN	Symbol	Function
1	VR	Reference voltage	2	IN	Input
3	GND	Ground	4	OD	Differential amplifier output
5	SC	Latch input	6	NR	Terminal for noise absorption
7	OS	Output	8	VS	Supply Voltage

### ABSOLUTE MAXIMUM RATINGS( $T_a = -20-80$ unless otherwise noted)

Symbol	Parameter	Conditions	Ratings	Unit
IS	Supply current		8	mA
Ivr	VR pin current	Between VR-IN Between VR-GND Between IN-VR	250 30 -250	mA
Iin	IN terminal current	Between IN-VR Between IN-GND Between VR-IN	250 30 -250	mA
Isc	SC terminal current		5	mA
Pd	Power dissipation		200	mW
Topr	Operating temperature		-20-80	°C
Tstg	Storage temperature		-55-125	°C

**ELECTRICAL CHARACTERISTICS (Ta=-20~80 unless otherwise noted)**

Symbol	Parameter	Test conditions	Temperature(°C)	Min	Typ	Max	Unit
$I_S$	Supply current	V <sub>S</sub> =12V, VR-VIN=30mV	-20 25 80		400	580 530 480	μA
V <sub>T</sub>	Trip voltage	V <sub>S</sub> =12V,VR-VIN	-20 ~ +80	4	6.1	9	mVRms
I <sub>IM1</sub>	Timed current 1	V <sub>S</sub> =12V,VR-VIN=30mV V <sub>O1</sub> =1.2V	25			-30	μA
I <sub>IM2</sub>	Timed current 2	V <sub>S</sub> =12V, V <sub>O2</sub> =0.8V	25	17		37	μA
I <sub>O</sub>	Output current	V <sub>SCM</sub> =1.4V Is1=580μA Is1=530μA V <sub>OS</sub> =0.8V Is1=480μA	-20 25 80	-200 -100 -75			μA
V <sub>SC</sub> "ON"	SC"ON"voltage	V <sub>S</sub> =12V	25	0.7		1.4	V
I <sub>SC</sub> "ON"	SC input current	V <sub>S</sub> =12V	25			5	μA
I <sub>OL</sub>	output low-level current	V <sub>S</sub> =12V,V <sub>O3</sub> =0.2V	-20 ~ +80	200			μA
V <sub>K</sub>	Input clamp voltage	V <sub>S</sub> =12V,I <sub>IC</sub> =20mA	-20 ~ +80	4.3		6.7	V
V <sub>dc</sub>	Differential input clamp voltage	I <sub>DC</sub> =100mA	-20 ~ +80	0.4		2	V
V <sub>"OFF"</sub>	Latch circuit is off-state supply voltage			25	0.5		V
T <sub>ON</sub>	Operating time	V <sub>S</sub> =12V,VR-VIN=0.3V	25	3		6	ms

**APPLICATION CIRCUIT**
