


Quadrature Demodulator

The quadrature demodulator is designed for IF/RF operation and has very low power consumption. Input frequencies in the range 20 to 300 MHz are allowed. The demodulator system has two gain stages, one before and one after the I/Q down-converters and the gain elements can be independently controlled. This flexible architecture allows the users to optimise characteristics depending on their system requirements. Optimum noise figure can be achieved by maximising gain in first gain stage and minimising gain in the second stage. Intermodulation performance can be optimised by decreasing gain in the first or second stages. A lower gain in the second gain stage will tend to reduce dc offsets in the output I/Q signal. Further detailed information on the effects of controlling gain stages is available in the CMX970 datasheet.




Typical system application utilising:

- CMX970—IF/RF Quadrature Demodulator
- CMX998—Cartesian Feedback Loop (CFBL) Transmitter
- CMX7861—Programmable Baseband Interface IC


Evaluation Support

The EV9700 is an Evaluation Kit designed for evaluating and demonstrating the capabilities of the CMX970 integrated circuit. All the circuits necessary to demonstrate the facilities provided by the IC, such as matching circuits, power supply regulators, etc are provided on the EV9700 board.

A C-BUS interface connector is provided for control of the EV9700 by a host microcontroller or CML PE0002 interface card. The CMX970 can also be used in a 'direct control' mode, where a host or PE0002 is not required. Alternatively any microcontroller evaluation/emulator kit can be used to drive the CMX970/EV9700 serial bus.



Package



Depending on the method of lead termination at the edge of the package, pull back (L1) may be present.
L minus L1 to be equal to, or greater than 0.3mm
The underside of the package has an exposed metal pad which should ideally be soldered to the pcb to enhance the thermal conductivity and mechanical strength of the package fixing. Where advised, an electrical connection to this metal pad may also be required

Mechanical Outline of the 16-pin VQFN (Q7)

Order as part no. **CMX970Q7**

Electrical Specification Summary

Operating Limits	Min	Typ	Max	Unit
Supply Voltage:				
Digital Supply ($V_{DD} - V_{SS}$)	3.0	3.3	3.6	V
Analogue Supply ($V_{CC} - V_{RF\text{GND}}$)	3.0	3.3	3.6	V
Operating Temperature	-40	-	+85	°C
Local Oscillator Input	40	-	500	MHz
RF/IF Input	20	-	300	MHz

DC Parameter - Supply Current	Min	Typ	Max	Unit
Total Current Consumption:				
Powersave mode	-	10	-	µA
Bias only	-	1.5	-	mA
Operating	-	15	-	mA

IF/RF Amplifier and Quadrature Demodulator	Min	Typ	Max	Unit
Performance Figures:				
Gain	-	56	-	dB(V/V)
Noise figure	-	10	-	dB
Third order intercept point (input)	-	-15	-	dBm

Comprehensive technical datasheet and support material is available from the CML website.

Click here to link to the [CML website](#) or search for: CMX970

FirmASIC, FirmCODEC, RALCWI, Function Image and DuraTALK are trademarks of CML Microsystems Plc.

	 CML Microcircuits (UK) Ltd <small>COMMUNICATION SEMICONDUCTORS</small>	 CML Microcircuits (USA) Inc. <small>COMMUNICATION SEMICONDUCTORS</small>	 CML Microcircuits (Singapore) Pte Ltd <small>COMMUNICATION SEMICONDUCTORS</small>
Phone:	+44 (0) 1621 875500	+1 336 744 5050 800 638 5577	+65 62 888129
Fax:	+44 (0) 1621 875600	+1 336 638 5577	+65 62 888230
Email Sales:	Sales@cmlmicro.com	us.sales@cmlmicro.com	sg.sales@cmlmicro.com
Email Tech Support:	techsupport@cmlmicro.com	us.techsupport@cmlmicro.com	sg.techsupport@cmlmicro.com
www.cmlmicro.com			
Search for: cmlmicro			