

Digital Attenuator, 1-Bit, 15 dB DC - 2.0 GHz

Rev. V4

Features

- Single 15-dB Step
- Low Loss, 0.3 dB Typical @ 900 MHz
- 2.5 to 5.0 Volt Operation
- SOT-25 Plastic Package
- Tape and Reel Packaging Available

Description

M/A-COM's AT-267 is a 1-bit, 15-dB step GaAs MMIC digital attenuator in a low cost SOT-25, 5 lead surface mount plastic package. The AT-267 is ideally suited for use where high accuracy, very low power consumption and low intermodulation products are required.

Typical applications include wireless handsets, base stations, wireless LAN equipment, GPS receivers and any RF applications with automatic gain/level control circuits.


The AT-267 is fabricated as a monolithic GaAs integrated circuit using a mature PHEMT process. The process features full chip passivation for performance and reliability.

Ordering Information ¹

Part Number	rt Number Package	
AT-267TR	Tape and Reel (1K Reel)	
AT-267TR-3000	Tape and Reel (3K Reel)	
AT-267SMB	Sample Board	

^{1.} Reference Application Note M513 for reel size information.

Functional Schematic



Pin Configuration

Pin No.	Function	Pin No.	Function
1	RF1	4	V1
2	Ground	5	V2
3	RF2		

Absolute Maximum Ratings ²

Parameter	Absolute Maximum		
Input Power	+21 dBm		
Control Voltage	V _C ≤ 8V		
Operating Temperature	-40°C to +85°C		
Storage Temperature	-65°C to +150°C		

^{2.} Exceeding any one or combination of these limits may cause permanent damage to this device.

[•] Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300

Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298
 Visit www.macomtech.com for additional data sheets and product information.



Digital Attenuator, 1-Bit, 15 dB DC - 2.0 GHz


Rev. V4

Electrical Specifications³: $T_A = 25^{\circ}C$, $V_C = +2.5$ Volts, $Z_0 = 50$ Ω

Parameter	Test Conditions	Units	Min	Тур	Max
Insertion Loss (Reference State)	1.0 GHz 2.0 GHz	dB	_	0.3 0.4	0.4 0.5
Attenuation	1.0 GHz 2.0 GHz	dB dB	14.6 14.4	15.1 14.9	15.6 15.4
VSWR	1.0 GHz 2.0 GHz	Ratio Ratio	_	1.2:1 1.3:1	_
Input IP ₃	1.0 GHz Insertion Loss State Attenuation State	dBm dBm	40 40	50 50	
P _{1dB}	1.0 GHz Insertion Loss State Attenuation State	dBm dBm	24 20	26 23	_
Control Current	_	μA	_	_	10
Trise, Tfall	10% to 90% RF, 90% to 10% RF	nS	_	29	_
Ton, Toff	50% Control to 90% RF, 50% Control to 10% RF	nS	_	50	_
Transients	In-band	mV	_	10	_

^{3.} For positive voltage control, external DC blocking capacitors are required on all RF ports (pins 1, 2 and 3).

SOT-25




Truth Table 4,5

Mode (Control)	V1	V2	Attenuation
Positive ⁴	0 ± 0.2V	+2.5V to +5V	15 dB
	+2.5V to +5V	0 ± 0.2V	Reference State
Negative ⁵	0 ± 0.2V	-2.5V to -5V	Reference State
	-2.5V to -5V	0 ± 0.2V	15 dB

- 4. External DC blocking capacitors are required as noted.
- 5. If negative control is used, DC blocking capacitors are not required on RF ports and ground.

Positive Control Voltage Schematic



- ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results,
- and/or prototype measurements. Commitment to develop is not guaranteed.

 PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.
- North America Tel: 800.366.2266 / Fax: 978.366.2266
- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298 Visit www.macomtech.com for additional data sheets and product information.




Digital Attenuator, 1-Bit, 15 dB DC - 2.0 GHz


Rev. V4

Typical Performance Curves


Insertion Loss vs. Frequency over Temperature with Negative Control




Attenuation vs. Frequency over Temperature with Negative Control




VSWR, 0 and 15 dB States with Negative Control at +25°C




Insertion Loss vs. Frequency over Temperature with Positive Control



Attenuation vs. Frequency over Temperature with Positive Control



VSWR, 0 and 15 dB States with Positive Control at +25°C



- ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

 PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology
- PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.
- North America Tel: 800.366.2266 / Fax: 978.366.2266
- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298
 Visit www.macomtech.com for additional data sheets and product information.

M/A-COM Technology Solutions Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.