

MODEM MAGNETICS

V.90 Modem Transformer


TM00409

- Provides isolation and balance while minimizing signal distortion and insertion loss in high speed modem applications
- Designed to match a 600Ω line to a 360Ω load
- Qualified per Bellcore TR-TSY-000357-1
- Designed to provide supplementary insulation at a working voltage of 250V
- Approved by UL, CSA and BABT
- Minimum interwinding breakdown voltage of 1500 Vrms


ELECTRICAL SPECIFICATIONS at 25° C

Part Number	Turns Ratio ± 2%	Insertion Loss dB	Return Loss dB	Frequency Response dB	DCR Ω max		Harmonic Distortion dB	Longitudinal Balance dB
		@ 1 kHz	200 Hz - 3500 Hz	100 Hz - 4 kHz	Pri	Sec	-3dBm, 150 Hz	200 Hz - 3500 Hz
2811B	1 : 1	≤ 2.1	≥ 20	≤ 0.1	135	135	≤ -75	≥ 60

SCHEMATIC




TYPICAL SPICE TRANSMISSION MODEL



MODEM MAGNETICS V.90 Modem Transformer

MECHANICAL

2811B



Note: Unless otherwise specified, dimensions are nominal and in inches [millimeters].

©2000 Bel Fuse Inc. Specifications subject to change without notice. 05.00

CORPORATE

Bel Fuse Inc.
198 Van Vorst Street
Jersey City, NJ 07302
Tel 201-432-0463
Fax 201-432-9542
www.belfuse.com

FAR EAST

Bel Fuse Ltd.
8F / 8 Luk Hop Street
San Po Kong
Kowloon, Hong Kong
Tel 852-2328-5515
Fax 852-2352-3706
www.belfuse.com

EUROPE

Bel Fuse Europe Ltd.
Preston Technology Management Centre
Marsh Lane, Suite G7, Preston
Lancashire, PR1 8UD, U.K.
Tel 44-1772-556601
Fax 44-1772-888366
www.belfuse.com