



ELECTRONICS, INC.  
44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089  
<http://www.nteinc.com>

## NTE1142 Integrated Circuit FM Multiplex Stereo Decoder

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Supply Voltage, $V_{CC}$ .....	15V
Supply Current, $I_{CC}$ .....	18mA
Lamp Driver Current, $I_L$ .....	100mA
Power Dissipation, $P_D$ .....	400mW
Operating Temperature Range ( $V_{CC} = 12\text{V}$ ), $T_{opr}$ .....	-10 to $+75^\circ\text{C}$
Storage Temperature Range, $T_{stg}$ .....	-40 to $+125^\circ\text{C}$

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Standby Current	$I_{CC}$	$V_{CC} = 12\text{V}$	-	10	18	mA
Input Impedance	$Z_i$	$f = 1.0\text{kHz}$	-	20	-	$\text{k}\Omega$
Stereo Channel Separation	Sep	$f = 100\text{kHz}$ (Note 1)	-	35	-	dB
		$f = 1.0\text{kHz}$	30	45	-	dB
		$f = 10\text{kHz}$ with $15\text{kHz}$ LPF	-	30	-	dB
Voltage Gain	$A_V$	$38\text{kHz}$ BEF	-	-1.5	-	dB
Channel Balance	Ch. B	Monoaural Input, $f = 1.0\text{kHz}$	-	0.2	2.0	dB
Total Harmonic Distortion	THD		-	0.5	1.0	%
Audio Muting Voltage (Required at Pin 5)	Mute On		0.6	0.85	-	V
	Mute Off		-	1.08	1.5	V
Lamp Indictaor Input Level	Lamp ON		-	12	22	$\text{mV}_{\text{rms}}$
	Lamp Off		-	8.4	-	$\text{mV}_{\text{rms}}$
Stereo-Monaural Switching Voltage (Required at Pin 4)	Stereo		-	1.13	1.5	V
	Mono		0.6	0.82	-	V
Ultrasonic Frequency Rejection		19kHz (Note 2)	-	30	-	dB
		38kHz (Note 2)	-	25	-	dB
Inherent SCA Rejection	$SCA_{\text{rej}}$	without filter	-	55	-	dB
Attenuation in Muting Mode		(Note 3)	45	55	-	dB

Note 1. Measurement made with  $200\text{mV}_{\text{rms}}$  Standard Multiplex Composite Signal Containing Left (45%) and Right (45%) audio information with a 10% (19kHz) pilot signal. Modulation frequency is  $1.0\text{kHz}$  unless otherwise specified.

Note 2. Referenced to  $1.0\text{kHz}$  output signal with Standard Multiplex Composite Input Signal.

Note 3. Referenced to  $1.0\text{kHz}$  output signal with either Standard Multiplex Composite or Monoaural Input Signal.

**Pin Connection Diagram**  
(Front View)

19kHz Tank	1	14	Filter Network
19kHz Tank	2	13	38kHz Tank
Input	3	12	Rt Channel Output
Stereo Switch	4	11	Lt Channel Output
Mute Switch	5	10	38kHz Tank
Lamp Drive	6	9	V <sub>CC</sub>
GND	7	8	N.C.

