



*SYM53C040* Data Sheet

# Symbios **SYM53C040**

## *Enclosure Services Processor*

### Overview

The SYM53C040 is a highly integrated single-chip enclosure services processor, with the flexibility to implement SCSI drive enclosure management functions such as SAF-TE (SCSI Accessed Fault-Tolerant Enclosure) or SES (SCSI-3 Enclosure Services). The industry standard SAF-TE and SES protocols are used to detect drive presence, conditioning a slot for drive insertion/removal, fan speed control, power supply voltage monitoring, door lock status and usage statistics.

### Hardware Features

- A flexible single-chip processor solution capable of implementing SAF-TE or SES protocols AND working in either parallel SCSI or serial Fibre Channel environments
- Integrated LVDlink™ transceivers for direct attach to either low voltage differential (LVD) or single-ended (SE) SCSI busses
- Supports the SFF-8067 environment interface for Fibre Channel enclosures
- Programmable multi-purpose I/O pins (MPIO) and multi-purpose LED pins (MPLED) for OEM specific monitoring
  - 28 MPIO for enclosure sensory inputs
  - 24 MPLED with programmable blink rates for displaying status events
- Two multi-master 2 wire serial interfaces for chip configuration, firmware downloading, and access to external 2 wire peripherals

- Recommended for use with SYM53C120 and/or SYM53C141 SCSI bus expanders
- Integrated MCS® 51 micro controller
- Internal SYM53C80 SCSI protocol controller
- Ability to set SCSI ID in upper byte lane
- IEEE 1149.1 JTAG compliant
- Packaged in a 160 PQFP or 169 PBGA

### Applications

- Server clustering environments
- JBOD or RAID storage enclosures
- Fibre Channel or SCSI enclosures

Figure 1 on page two, is an example of a SCSI storage enclosure implementing the SYM53C040, the SYM53C141/120 SCSI bus expanders, and the SYM8951U/22910 PCI-Ultra2 SCSI host adapters. By way of the MPIO pins, the SYM53C040 monitors the environment within the enclosure, such as temperature, power supply status, disk slot status, etc. Then, during regular intervals, the status information is sent to the host controller via the SCSI bus. Likewise, in response to commands sent by the host controller, the SYM53C040 uses the MPIO and MPLED pins to enable or disable enclosure elements, such as disk slots, enclosure key lock, individual drive key locks, indicator displays, SCSI bus expanders, etc.




Figure 1: SCSI storage enclosure




Figure 2: Fibre Channel storage enclosure

Figure 2 is an example of a Fibre Channel storage enclosure implementing the SYM53C040. As in Figure 1, the SYM53C040 is collecting sensory inputs and reporting this information back to the host system. However, in this configuration, it communicates this information via the SFF-8067 interface. The drive acts as a conduit in passing commands and data between the host and enclosure.




Figure 3: SYM53C040 block diagram

Figure 3 shows the functional block diagram for the SYM53C040. In order to achieve functionality and flexibility, the SYM53C040 incorporates an integrated SYM53C80 SCSI protocol controller, a MCS-51 family compatible micro controller, internal Static RAM, two 2 wire serial interfaces and multi-purpose I/O registers connected to the MPIO and MPLED pins. Below is a brief description of each element.

### SYM53C80:

The SYM53C80 is an 8-bit asynchronous SCSI core which supports ultra SCSI speeds. The core contains support for a DMA interface and additional support for micro controller interrupts. The SYM53C040 uses the dedicated DMA interface and MCS® 51 micro controller for memory accesses to/from the SCSI core.

### Micro Controller:

The micro controller is an 8-bit Intel MCS® 51 compatible device. The micro controller is operated with a 20 MHz CPU clock in the SYM53C040 derived from the 40 MHz ESP system clock. This micro controller uses a shared address/data bus and can address either 64K of shared program and data memory or 64 K each of separate program and data memory spaces.

### 2 Wire Serial Interfaces:

The SYM53C040 has two 2 wire Serial Interface blocks. Access to external serial EEPROM storage and any other user-defined 2 wire peripheral devices is provided by the 2 wire Serial Interface blocks. As a default, the SYM53C040 will attempt to download from an external serial configuration ROM through one 2 wire interface at power-on or after a reset.

### MPIO Banks:

The SYM53C040 provides up to 28 separate multi-purpose I/O (MPIO) signal pins and 24 multi-purpose LED (MPLED) pins. For design flexibility, the MPLED pins can, if desired, be used as additional multi-purpose

I/O pins. The I/O pins are firmware programmable to configure the SYM53C040 to meet many possible monitoring combinations. As a result, numerous configurations of drives, fans, and power supplies can be supported given the total number of MPIO and MPLED pins.

### SFF-8067 Mode Control & Logic Interface:

This mode is a configuration option determined at power on. In operation, the SFF-8067 interface is used instead of the SCSI interface. A transfer sequence is initiated upon assertion of Parallel\_ESI by the drive. The host initiates all read and write operations. The drive does not initiate any activity, but does control the bi-directional interface. The back plane uses SEL\_N to specify the loop identifier for the drive.




Figure 4: Functional signal grouping

## Technical Information

|                         |                                                                         |
|-------------------------|-------------------------------------------------------------------------|
| Firmware protocol:      | SAF-TE, SES                                                             |
| Monitoring capability:  | 28 programmable MPIO pins<br>24 programmable MPLED pins                 |
| Input clock:            | 40 MHz                                                                  |
| Package:                | 160 Plastic Quad Flat Pack (PQFP)<br>169 Plastic Ball Grid Array (PBGA) |
| Complementary products: | SYM53C120 (SE to SE or SE to HVD)<br>SYM53C141 (SE to SE or SE to LVD)  |
|                         | For electrical and logical isolation of SCSI Bus segments               |

## LSI Logic Sales Offices and Design Resource Centers

LSI Logic Corporation  
Corporate Headquarters  
Tel: 408.433.8000

### NORTH AMERICA

#### California

Irvine  
• Tel: 949.553.5600  
Fax: 949.474.8101

San Diego  
Tel: 619.613.8300  
Fax: 619.613.8350

Wireless Design Center  
Tel: 619.350.5560  
Fax: 619.350.0171

Silicon Valley  
• Tel: 408.433.8000  
Fax: 408.954.3353

#### Colorado

Boulder  
Tel: 303.447.3800  
Fax: 303.541.0641

#### Florida

Boca Raton  
Tel: 561.989.3236  
Fax: 561.989.3237

#### Georgia

Atlanta  
Tel: 770.641.8001  
Fax: 770.641.8805

#### Illinois

Schaumburg  
• Tel: 847.995.1600  
Fax: 847.995.1622

#### Kentucky

Bowling Green  
Tel: 502.793.0010  
Fax: 502.793.0040

#### Maryland

Bethesda  
Tel: 301.897.5800  
Fax: 301.897.8389

#### Massachusetts

Waltham  
• Tel: 781.890.0180  
Fax: 781.890.6158

#### Minnesota

Minneapolis  
• Tel: 612.921.8300  
Fax: 612.921.8399

#### New Jersey

Edison  
• Tel: 732.549.4500  
Fax: 732.549.4802

#### New York

New York  
Tel: 716.218.0020  
Fax: 716.218.9010

#### North Carolina

Raleigh  
Tel: 919.785.4520  
Fax: 919.783.8909

#### Oregon

Beaverton  
Tel: 503.645.0589  
Fax: 503.645.6612

#### Texas

Austin  
Tel: 512.388.7294  
Fax: 512.388.4171

#### Dallas

• Tel: 972.503.3205  
Fax: 972.503.2258

#### Houston

Tel: 281.379.7800  
Fax: 281.379.7818

#### Plano

Tel: 972.244.5000  
Fax: 972.509.0349

#### Washington

Issaquah  
Tel: 425.837.1733  
Fax: 425.837.1734

#### Canada

##### Ontario

Ottawa  
• Tel: 613.592.1263  
Fax: 613.592.3253

##### Toronto

• Tel: 416.620.7400  
Fax: 416.620.5005

##### Quebec

Montreal  
• Tel: 514.694.2417  
Fax: 514.694.2699

### INTERNATIONAL

#### Australia

New South Wales  
Reptechnic Pty Ltd  
• Tel: 612.9953.9844  
Fax: 612.9953.9683

#### China

Beijing  
LSI Logic International  
Services Inc  
Tel: 86.10.6804.2534.40  
Fax: 86.10.6804.2521

#### Denmark

Ballerup  
LSI Logic Development  
Centre  
Tel: 45.44.86.55.55  
Fax: 45.44.86.55.56

#### France

Paris  
LSI Logic S.A.  
Immeuble Europa  
• Tel: 33.1.34.63.13.13  
Fax: 33.1.34.63.13.19

#### Germany

Munich  
LSI Logic GmbH  
• Tel: 49.89.4.58.33.0  
Fax: 49.89.4.58.33.108

#### Stuttgart

Tel: 49.711.13.96.90  
Fax: 49.711.86.61.428

#### Hong Kong

Hong Kong  
AVT Industrial Ltd  
Tel: 852.2428.0008  
Fax: 852.2401.2105

#### India

Bangalore  
LogiCAD India Private Ltd  
• Tel: 91.80.664.5530  
Fax: 91.80.664.9748

#### Israel

Ramat Hasharon  
LSI Logic  
• Tel: 972.3.5.480480  
Fax: 972.3.5.403747

#### Netanya

VLSI Development Centre  
Tel: 972.9.657190  
Fax: 972.9.657194

#### Italy

Milano  
LSI Logic S.P.A.  
• Tel: 39.039.687371  
Fax: 39.039.6057867

#### Japan

Tokyo  
LSI Logic K.K.  
• Tel: 81.3.5463.7821  
Fax: 81.3.5463.7820

#### Osaka

• Tel: 81.6.947.5281  
Fax: 81.6.947.5287

#### Korea

Seoul  
LSI Logic Corporation of  
Korea Ltd  
• Tel: 82.2.528.3400  
Fax: 82.2.528.2250

#### The Netherlands

Eindhoven  
LSI Logic Europe Ltd  
Tel: 31.40.265.3580  
Fax: 31.40.296.2109

#### Singapore

Singapore  
LSI Logic Pte Ltd  
• Tel: 65.334.9061  
Fax: 65.334.4749

#### Sweden

Stockholm  
LSI Logic AB  
• Tel: 46.8.444.15.00  
Fax: 46.8.750.66.47

#### Switzerland

Brugg/Biel  
LSI Logic Sulzer AG  
Tel: 41.32.536363  
Fax: 41.32.536367

#### Taiwan

Taipei  
LSI Logic Asia-Pacific  
• Tel: 886.2.2718.7828  
Fax: 886.2.2718.8869

Avnet-Mercuries  
Corporation, Ltd  
Tel: 886.2.2503.1111  
Fax: 886.2.2503.1449

Jeilin Technology  
Corporation, Ltd  
Tel: 886.2.2248.4828  
Fax: 886.2.2242.4397

Lumax International  
Corporation, Ltd  
Tel: 886.2.2788.3656  
Fax: 886.2.2788.3568

#### United Kingdom

Bracknell  
LSI Logic Europe Ltd  
• Tel: 44.1344.426544  
Fax: 44.1344.481039

• Sales Offices with Design Centers

LSI Logic logo design, The System on a Chip Company are registered trademarks, Symbios, and IVDlink are trademarks of LSI Logic Corporation. All other brand and product names may be trademarks of their respective companies.

LSI Logic Corporation reserves the right to make changes to any products and services herein at any time without notice. LSI Logic does not assume any responsibility or liability arising out of the application or use of any product or service described herein, except as expressly agreed to in writing by LSI Logic; nor does the purchase, lease, or use of a product or service from LSI Logic convey a license under any patent rights, copyrights, trademark rights, or any other of the intellectual property rights of LSI Logic or of third parties.

©1998 by LSI Logic Corporation. All rights reserved.  
An ISO 9001 Registered Company

Printed in the U.S.A.  
T71981I 798 2M

www.lsillogic.com

