		<u> </u>
REPARED BY: DATE:		SPEC.No: DG-996011
2/ ht Jun 8 /1979	SMARP	ISSUE Jun/8/99
. ramoshna		PAGE 14 pages
PPROVED BY: DATE: $T_{im} = 9 / 99$	ELECTRONIC COMPONENTS GRO	OUP REPRESENTATIVE DIVISION:
and a line		T Opto-Electronic Devices Division
M. Omoto	SPECIFICATION	N I ·
	-	
DEVICE	SPECIFICATION FOR	
	Light Emitting Diode)
MODEL	NI_	
MODEL		
l	LIIZE40A)
	· · · · · · · · · · ·	
1. These specification sheets inclu Please do not reproduce or cause	ide materials protected under the copyrig	ht of Sharp Corporation ("Sharp").
		ip's consent.
2. When using this product, please	observe the absolute maximum ratings a	and the instructions for use outlined
In these checitication cheets of	well as the precautions mentioned below	. Sharp assumes no responsibility
for any domage resulting from a		with the absolute maximum ratings
for any damage resulting from u and the instructions included in	these specification sheets and the preca	utions mentioned below
for any damage resulting from u and the instructions included in	these specification sheets, and the preca	utions mentioned below.
for any damage resulting from u and the instructions included in (Precautions)	these specification sheets, and the preca	utions mentioned below.
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig	these specification sheets, and the precar ned for use in the following application a	utions mentioned below.
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunication	these specification sheets, and the precar ned for use in the following application a * Audio visual equipment * Home app	utions mentioned below. reas; liance
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines	these specification sheets, and the precar ned for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers	utions mentioned below. reas; liance equipment
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines	these specification sheets, and the precar ned for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equi-	utions mentioned below. reas; liance equipment
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su	these specification sheets, and the precation and for use in the following application a Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the	utions mentioned below. reas; liance equipment juipment listed in paragraphs ose respective paragraphs.
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su	these specification sheets, and the precation ned for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail as fa design and redundant d	utions mentioned below. reas; liance equipment juipment listed in paragraphs ose respective paragraphs.
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the sofety design of the	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de	utions mentioned below. reas; liance equipment juipment listed in paragraphs ose respective paragraphs. lesign considering
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be	utions mentioned below. reas; liance equipment juipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability and high reliability and
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and	these specification sheets, and the precation ned for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the , such as fail-safe design and redundant d e overall system and equipment, should be roduct is used for equipment which dema precision such as	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation com	these specification sheets, and the precation and for use in the following application a Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; trol and safety equipment (aircraft, train	utions mentioned below. reas; liance equipment puipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and a automobile etc.)
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; atrol and safety equipment (aircraft, train * Gas leakage sensor breakers * Rescue	utions mentioned below. reas; liance equipment puipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and , automobile etc.) e and security equipment
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the , such as fail-safe design and redundant d e overall system and equipment, should b roduct is used for equipment which dema precision, such as ; atrol and safety equipment (aircraft, train 6 Gas leakage sensor breakers * Rescue ment	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and , automobile etc.) e and security equipment
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; atrol and safety equipment (aircraft, train * Gas leakage sensor breakers * Rescue ment	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and a automobile etc.) e and security equipment
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; ntrol and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as :	utions mentioned below. reas; liance equipment guipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and , automobile etc.) e and security equipment remely high reliability
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; atrol and safety equipment (aircraft, train * Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the * Telecommunication equipment (for the * Computers * Computer	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and and security equipment remely high reliability runk lines)
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the , such as fail-safe design and redundant d e overall system and equipment, should b roduct is used for equipment which dema precision, such as ; throl and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the trol equipment * Medical equipment	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and a automobile etc.) e and security equipment remely high reliability runk lines)
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and cor	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; trol and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the torol equipment * Medical equipment sult with a Sharp sales representative if t	utions mentioned below. reas; liance equipment puipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and and security equipment remely high reliability runk lines) here are any questions
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and con regarding interpretation	these specification sheets, and the precation these specification sheets, and the precation Audio visual equipment * Home approved approved the precation areas is for equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment of the precations given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; atrol and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the atrol equipment * Medical equipment sult with a Sharp sales representative if to n of the above three paragraphs.	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and and security equipment remely high reliability runk lines) here are any questions
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and consult with	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the , such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; throl and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the throl equipment * Medical equipment sult with a Sharp sales representative if to n of the above three paragraphs. a Sharp sales representative for any question * Audio visual equipment is an expresentative for any question * and precision is the same paragraphs.	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and a automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and con regarding interpretation 3. Please contact and consult with	these specification sheets, and the precation and for use in the following application a * Audio visual equipment * Home app on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; throl and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the torol equipment * Medical equipment sult with a Sharp sales representative if t n of the above three paragraphs. a Sharp sales representative for any quest	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and a automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product.
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and consult with	these specification sheets, and the precation these specification sheets, and the precation Audio visual equipment * Home approved Audio visual equipment * Home approved approved to the precation areas is for equipment (Terminal) * Measuring * Computers at in the above application areas is for equipment of the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which demains precision, such as ; atrol and safety equipment (aircraft, train and precision, such as ; * Telecommunication equipment (for the and precision, such as ; * Telecommunication equipment (for the atrol equipment * Medical equipment sult with a Sharp sales representative if the n of the above three paragraphs. a Sharp sales representative for any question DA	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and and shigh reliability and and security equipment remely high reliability runk lines) here are any questions tions about this product.
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and con regarding interpretation 3. Please contact and consult with	these specification sheets, and the precation these specification sheets, and the precation Audio visual equipment * Home approved approved the precation areas is for equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; there are a search of the equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the there are a sharp sales representative if to n of the above three paragraphs. a Sharp sales representative for any quest DA DA	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product. TE: Tunt & 1/989 ESENTED BY:
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and con regarding interpretatio 3. Please contact and consult with CUSTOMER'S APPROVAL	these specification sheets, and the precation these specification sheets, and the precation Audio visual equipment * Home appin on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; throl and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the throl equipment * Medical equipment sult with a Sharp sales representative if to n of the above three paragraphs. a Sharp sales representative for any quest DA PRI	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and a, automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product. TE: Juni d 1/989 ESENTED BY: Matchedit
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and consult with CUSTOMER'S APPROVAL	these specification sheets, and the precation these specification sheets, and the precation Audio visual equipment * Home appin on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; throl and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the throl equipment * Medical equipment usult with a Sharp sales representative if to n of the above three paragraphs. a Sharp sales representative for any quest DA PRI	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and a automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product. TE: Junid 11889 ESENTED BY: Junid 11889 Katoh.
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and consult with CUSTOMER'S APPROVAL DATE:	these specification sheets, and the precation these specification sheets, and the precation Audio visual equipment * Home approved approved the precation areas is for equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment of the precations given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which demains precision, such as ; throl and safety equipment (aircraft, trained Gas leakage sensor breakers * Rescute ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the throl equipment * Medical equipment sult with a Sharp sales representative if the n of the above three paragraphs. a Sharp sales representative for any question DA PRE	utions mentioned below. reas; liance equipment puipment listed in paragraphs lose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and a, automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product. TE: Te: Te: Te: Te: Te: Te: Te: Te
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and consult with CUSTOMER'S APPROVAL DATE:	these specification sheets, and the precation these specification sheets, and the precation Audio visual equipment * Home approved approved the precation areas is for equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which demains precision, such as ; there are a strain the former of the second ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the there are paragraphs. a Sharp sales representative for any question DA PRI DA PRI M.K. Dep Eng	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and and shigh reliability and a automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product. TE: Tuni d 1/989 ESENTED BY: Mattack Katoh, partment General Manager of tineering Dept., III
for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and con regarding interpretation 3. Please contact and consult with CUSTOMER'S APPROVAL DATE:	these specification sheets, and the precation these specification sheets, and the precation Audio visual equipment * Home approved approved the precation areas is for equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; the Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the the above three paragraphs. a Sharp sales representative for any quest DA PRI DA PRI	utions mentioned below. reas; liance equipment uipment listed in paragraphs ose respective paragraphs. lesign considering be taken to ensure reliability ands high reliability and and shigh reliability and a automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product. TE: Tuni d 1/SPS ESENTED BY: Mathematical Catoh, partment General Manager of pineering Dept.,III o-Electronic Devices Division
In these specification sheets, as for any damage resulting from u and the instructions included in (Precautions) (1) This products is desig * OA equipment * Telecommunicatio * Tooling machines If the use of the produ (2) or (3), please be su (2) Appropriate measures the safety design of th and safety when this p safety in function and * Transportation con * Traffic signals * Other safety equip (3) Please do not use this and safety in function * Space equipment * Nuclear power cor (4) Please contact and con regarding interpretation 3. Please contact and consult with CUSTOMER'S APPROVAL DATE: BY:	these specification sheets, and the precation these specification sheets, and the precation * Audio visual equipment * Home approved on equipment (Terminal) * Measuring * Computers ct in the above application areas is for equipment to observe the precautions given in the such as fail-safe design and redundant de e overall system and equipment, should be roduct is used for equipment which dema precision, such as ; throl and safety equipment (aircraft, train Gas leakage sensor breakers * Rescue ment product for equipment which require extra and precision, such as ; * Telecommunication equipment (for the throl equipment * Medical equipment asult with a Sharp sales representative if to n of the above three paragraphs. a Sharp sales representative for any quest M.K Dep Eng Opt Elector	utions mentioned below. reas; liance equipment uipment listed in paragraphs lesign considering be taken to ensure reliability ands high reliability and a, automobile etc.) e and security equipment remely high reliability runk lines) here are any questions tions about this product. TE: Juni d 1/989 ESENTED BY: Mathematical Katoh, bartment General Manager of gineering Dept.,III o-Electronic Devices Division ctronic Components Group

Feb/22/99 DG -996011 MODEL No. PAGE 1/14LT1ZE40A SHARP LT1ZE40A Specification 1. Application This specification applies to the light emitting diode device Model No. LT1ZE40A. [AlInGaP (dicing or scribe/brake type / Yellow green) chip LED device] 2. Outline dimensions and terminal connections Refer to the attached sheet Page 2. 3. Ratings and characteristics Refer to the attached sheet Page 3~5. 3-1. Absolute maximum ratings 3-2. Electro-optical characteristics 3-3. Derating Curve 3-4. Characteristics Diagram 4. Reliability Refer to the attached sheet Page 6. 4-1. Test items and test conditions 4-2. Failure judgement criteria 5. Incoming inspectionRefer to the attached sheet Page 7. 5-1. Inspection method 5-2. Description of inspection and criteria 6. Taping specificationRefer to the attached sheet Page 8~11. 6-1. Taping 6-2. Label 6-3. Luminous intensity rank 6-4. Dominant wavelength rank 7. Packing Specification Refer to the attached sheet Page 12. 7-1. Dampproof package 7-2. Storage conditions 7-3. Treatment after opening 8. Soldering Refer to the attached sheet Page 13. 8-1. Reflow soldering 8-2. Manual soldering 9. Precautions for use Refer to the attached sheet Page 14. 9-1. Precautions matters for designing circuit 9-2. Cleaning method 10. Environment Refer to the attached sheet Page 14. 10-1. Ozonosphere destructive chemicals. 10-2. Bromic non-burning materials



DG-	996	011	
DEL No.	in.		

LTIZE40A 3/14

MO

PAGE

Feb/22/99

3

SHARP

3. Ratings and characteristics

3-1. Absolute maximum ratings							
Parameter		Symbol		Rating			
Power dissipation		Р		78		mW	
Continuous forwa	rd current	IF		30		mA	
Peak forward current(Note 1)		I _{FM}	50		mA		
Derating factor DC		-	0.4			mA∕℃	
	Pulse	- 0.67			mA/℃		
Reverse voltage		V _R	5		V		
Operating temperature		Торг	-30	~	85	°C	
Storage temperati	ие	Tstg	-40 ~ 100			°C	
Soldering tempera	ature(Note 2)	Tsol	350			°C	

(Note1) Duty ratio=1/10,Pulse width=0.1ms

(Note2) Manual soldering Max.3second

3-2. Electro-optical character	istics		(Ta=25°C)				
Parameter	Symbol Conditions *2		MIN.	TYP.	MAX.	Unit	
Forward voltage	V _F		-	2.1	2.6	V	
Luminous intensity (Note 3)	Iv		10	28.2	-	mcd	
Peak emission wavelength	λp	IF=20mA	_	570	_	nm	
Dominant wavelength	λd		-	570	—	nm	
Spectrum radiation bandwidth	Δλ		-	15	-	nm	
Reverse current	I _R	VR=4V	-		100	μA	
Terminal capacitance	Ct	V=0V,f=1MHz		60	-	pF	

(Note 3)Measured by SHARP EG&G MODEL550(Radiometer/Photometersystem)

(Tolerance: $\pm 15\%$)





.

Jun/8/99 PAGE ^{-,} DG-996011 MODEL No.

LT1ZE40A

à y 6/14

1 5

NO.

4. Reliability

The reliability of products shall be satisfied with items listed below.

4-1. Test items and test c	Confidence l	evel: 90%	
Test items	Test conditions	Samples (n) Defective (C)	LTPD (%)
temperature cycling	-40°C(30min)~+100°C(30min),30times	n=22, C=0	10
High temp. and high humidity storage	Ta=+60°C, 90%RH, t=500h	n=22, C=0	10
High temperature storage	Ta=100°C,t=500h	n=22, C=0	10
Low temperature storage	Ta=-40°C,t=500h	n=22, C=0	10
Operating test	Ta=25°C,I _F =30mA,t=500h	n=22, C=0	10
Mechanical shock	15 000m/s ² , 0.5ms, 3times / ±X,±Y,±Z direction	n=11, C=0	20
Variable frequency vibration	200m/s ² , 100~2 000~100Hz/sweepfor 4min. ,4times/X,Y,Z direction	n=11, C=0	20
Soldering heat	Refer to the attached sheet, Page 13/14 2time	n=11, C=0	20

4-2. Failure judgement criteria *1

Parameter	Symbol	Failure judgement criteria *2
Forward voltage	V _F	$V_F > U.S.L. \times 1.2$
Reverse current	I _R	$I_R > U.S.L. \times 2.0$
Luminous intensity	Iv	Iv > The first stage value \times 2.0 or The first stage value \times 0.5 > Iv

*1: Measuring condition is in accordance with specification.

*2: U.S.L. is shown by Upper Specification Limit.

- 5. Incoming inspection
 - 5-1. Inspection method

A A single sampling plan, normal inspection level S-4 based on ISO 2859-1 shall be adopted.

Feb/22/99

7/14

PAGE

DG-996011

\$

LT1ZE40A

÷

Ĵ

MODEL No.

5-2. Description of inspection and criteria

No.	Inspection items	Criteria	Defect	AQL
1	Electro-optical characteristics	Not radiation		
2	Radiation color	Not correct		
3	Taping Product inserted in reverse direction		Major defect	0.1%
4	Label Model number is not printed, or misprinted			
5	Electrode plating Plating abnormality observed over 50% or greater percentage *1			
6	Electro-optical characteristics	Not conforming to the specification		
7	Outline dimensions	Not conforming to the specification		
8	Dust and flaw Effect to the specification		Minor defect	0.4%
9	Resin flash Over the unspecified tolerance			
10	Resin crack	0.3mm or greater from the product side face		
11	Solderbility	could solder 50% or greater and less than 90% out of judgement area *1		

*1 Judgement area : The plated area of the product bottom



Parameter		Symbol	Dimension [mm](TYP.)	Remarks
Concave square	Vertical	Α	1.55	Dimension excludes corner R
hole for part	Horizontal	В	2.3	at inside bottom
insertion	Pitch	P 1	4.0	
Round	Diameter	D _o	1.5	
sprocket	Pitch	Po	4.0	Accumulated error ±0.5mm/10 pitch
hole	Position	Ε	1.75	Distance between tape edge and hole center
Center to center	Vert.dire	P ₂	2.0	Center line of the concave square hole and
dimension	Hori.dire	F	3.5	round sprocket hole
Cover tape	Width	W ₁	5,5	
	Thickness	t 3	0.1	
Carrier tape	Width	Wo	8.0	
	Thickness	t 1	0.2	
Thickness of the entire u	nit	t ₂	1.2	With cover tape and carrier tape combined

X Material : Carrier tape ... PS, Cover tape ... Polyester

.



Parameter		Symbol	Dimension [mm](TYP.)	Remarks			
	Diameter		A	φ178			
Frange	Thickness		ge Thickness		t	1.5	
	Inner space direction		W	10	Dimension of shaft core		
	External di	ameter	В	\$ 60			
Hub	Spindle hol	le diameter	С	\$ 13			
	Key slit Width		E	2.0			
		Depth	U	4.5			
Notation 1	lotation for part name etc. Labeling on one side of flange.(part name,quantity,lot No.)			f flange.(part name,quantity,lot No.)			

X Material : Reel...Polystyrene





6-3.Luminous	ntensity ran		(Ta=25°C)		
Rank	Lun	ninous inte	nsity	Unit	Condition
A	10	~	19		
В	14	~	28	mcd	
С	21	~	40		I _F =20mA
D	30	~	30]	
E	43	~	84		

(Note 1) Also I shall not ask the delivery ratio of each rank.

6-4.Dominant	6-4.Dominant wavelength rank (Note 2)						
Rank	Domir	Dominant wavelength Unit					
d	562	~	566.0				
е	565.0	~	569				
f	568	~	572.0	nm	I _F =20mA		
g	571.0	~	575				

(Note 2) This rank value is the setting value of when that classifies it the rank and be not a guarantee value. Also I shall not ask the delivery ratio of each rank.

--

- 7. Packing specification
- 7-1. Dampproof package

In other to avoid the absorption of humidity in transport and storage, the device s are packed in aluminum sleeve.



Feb/22/99

12/14

PAGE

Ï

MODEL No.~ //

DG-996011

÷

٠. LT1ZE40A

7-2.Strage conditions

Temperature : 5 to 30℃ Humidity : less than 60%RH

7-3. Treatment after opening

(1) Please make a soldering within 15 days after opening under following condition;

Temperature : 5 to 30°C Humidity : less than 60%RH

- (2) In case the devices are not used for a long time after opening, the storage in dry box is recommendable. Or it is better to repack the devices with a desiccative by the sealer and put them in the some storage conditions as 7-2. Then they should be used within 2 weeks.
- (3) Please make a soldering after a following baking treatment if unused term should be over the conditions of (2)

*Recommendable conditions:

(1) in taping

Temprature:60°C to 65°C, Time:36 to 48 hours

2 in individual (on PWB or metallic tray)

Temprature: 100°C to 120°C, Time: 2 to 3 hours

8. Soldering

- 8-1.Reflow soldering
- (1) It is not recommended to exceed the soldering temperature and time shown below. Caused by substrate bend or the other mechanical stress during reflow soldering may happen gold wire disconnection etc. Therefore please check and study your solder reflow machine's best condition.
- (2) In case of 2 times reflow process,2nd reflow process should be done within 8 hours after 1st reflow process. (Strage condition ; at 30°C,RH less than 60%RH)
- (3) Reflow soldering temperature profile to be done under the following condition.





(4) Recommendable Metal Mask pattern for screen print Recommend 0.2mm to 0.3mm thickness metal mask for screen print. Caused by solder reflow condition, solder paste, substrate and the other material etc., may change solderbility.

Please check and study actual solderbility before usage.



Recommended soldar pattern (Unit:mm)

-DG-996011

KTIZE40A

MODEL No.

Feb/22/99

13/14

PAGE

8-2.Manual soldering

(1) It is recommended to keep the soldering iron temperature at 350°C (soldering iron power consumption 20W) and not to solder more than once or for over 3 seconds.

(2) When using a soldering iron, care must be taken not to damage the package. (Pay attention not to allow any under stress or heat on package.)

- 9. Precautions for use
- 9-1. Precautions matters for designing circuit

This product is not designed as electromagnetic and ionized-particle radiation resistant.

- 9-2. Cleaning method
- (1) Solvent cleaning

① Solvent temperature is not more than 45 degree. 2 Immersion up to 3 minutes. **Recommend conditions:** (2) Ultrasonic cleaning

The affect on the device from ultrasonic bath, ultrasonic output, duration, board size and device mounting method. Test the cleaning method under actual conditions and check for abnormalities before actual use.

Feb/22/99

PAGE

SADA

-996011

ETIZE40A

DG

MODEL No.

(3) Solvents

Use only the following types of solvent.

water, methyl alcohol, ethyl alcohol, isopropyl alcohol

Recommend conditions: R.T. 40KHz, 30W/1, 3 to 5 minutes

10. Environment

10-1. Ozonosphere destructive chemicals.

- (1) The device doesn't contain following substance.
- (2) The device doesn't have a production line whose process requires following substance. Restricted part: CFCs, halones, CCl4, Trichloroethane (Methychloroform)
- 10-2. Bromic non-burning materials

The device doesn't contain bromic non-burning materials(PBBOs,PBBs)