

NPN TIP100-101-102

SILICON DARLINGTON POWER TRANSISTORS

NPN epitaxial-base transistors in a monolithic Darlington circuit and housed in a TO-220 envelope. They are designed for general purpose amplifier and low-speed switching applications.

PNP complements are TIP105-106-107

Compliance to RoHS.

ABSOLUTE MAXIMUM RATINGS

Symbol	Ratings		Value	Unit	
V_{CBO}	Collector-Base Voltage		TIP100	60	V
			TIP101	80	
			TIP102	100	
V_{CEO}	Collector-Emitter Voltage		TIP100	60	V
			TIP101	80	
			TIP102	100	
V_{EBO}	Emitter-Base Voltage		TIP100	5	V
			TIP101		
			TIP102		
I_C	Collector Current		TIP100	8	A
			TIP101		
			TIP102		
I_{CM}	Collector Peak Current		TIP100	15	A
			TIP101		
			TIP102		
I_B	Base Current		TIP100	1	A
			TIP101		
			TIP102		
P_T	Power Dissipation	@ $T_c < 25^\circ$	TIP100	80	Watts
			TIP101		
			TIP102		
		@ $T_a < 25^\circ$	TIP100	2	
			TIP101		
			TIP102		
T_J	Junction Temperature		TIP100	150	$^\circ\text{C}$
			TIP101		
			TIP102		
T_s	Storage Temperature range		TIP100	-65 to +150	
			TIP101		
			TIP102		

NPN TIP100-101-102

THERMAL CHARACTERISTICS

Symbol	Ratings	Value	Unit
$R_{thJ-case}$	From junction-case	1.56	°C/W
$R_{thJ-amb}$	From junction-ambient	62.5	°C/W

ELECTRICAL CHARACTERISTICS

TC=25°C unless otherwise noted


Symbol	Ratings	Test Condition(s)		Min	Typ	Max	Unit
I_{CBO}	Collector Cutoff Current	$I_E = 0, V_{CB} = V_{CBOmax}$	TIP100	-	-	50	μA
			TIP101				
			TIP102				
I_{CEO}	Collector Cutoff Current	$I_E = 0, V_{CE} = 1/2 V_{CEOmax}$	TIP100	-	-	50	μA
			TIP101				
			TIP102				
I_{EBO}	Emitter Cutoff Current	$V_{EB} = 5\text{ V}, I_C = 0$	TIP100	-	-	8	mA
			TIP101				
			TIP102				
V_{CEO}	Collector-Emitter Breakdown Voltage (*)	$I_C = 30\text{ mA}, I_B = 0$	TIP100	60	-	-	V
			TIP101	80	-	-	
			TIP102	100	-	-	
$V_{CE(SAT)}$	Collector-Emitter saturation Voltage (*)	$I_C = 3\text{ A}, I_B = 6\text{ mA}$	TIP100	-	-	2	V
			TIP101				
			TIP102				
		$I_C = 8\text{ A}, I_B = 80\text{ mA}$	TIP100	-	-	2.5	
			TIP101				
			TIP102				
$V_{BE(on)}$	Base-Emitter Voltage (*)	$I_C = 8\text{ A}, V_{CE} = 4\text{ V}$	TIP100	-	-	2.8	V
			TIP101				
			TIP102				
h_{FE}	DC Current Gain (*)	$V_{CE} = 4\text{ V}, I_C = 3\text{ A}$	TIP100	1000	-	20k	-
			TIP101				
			TIP102				
		$V_{CE} = 4\text{ V}, I_C = 8\text{ A}$	TIP100	200	-	-	
			TIP101				
			TIP102				
C_{OB}	Output Capacitance	$I_E = 0, V_{CB} = 10\text{ V}$ $f = 1\text{ MHz}$	TIP100	-	-	200	pF
			TIP101				
			TIP102				

(*) Pulse Width $\approx 300 \mu s$, Duty Cycle $\angle 2.0\%$

NPN TIP100-101-102

MECHANICAL DATA CASE TO-220

DIMENSIONS (mm)		
	Min.	Max.
A	9,90	10,30
B	15,65	15,90
C	13,20	13,40
D	6,45	6,65
E	4,30	4,50
F	2,70	3,15
G	2,60	3,00
H	15,75	17,15
L	1,15	1,40
M	3,50	3,70
N	-	1,37
P	0,46	0,55
R	2,50	2,70
S	4,98	5,08
T	2,49	2,54
U	0,70	0,90



Pin 1 :	Base
Pin 2 :	Collector
Pin 3 :	Emitter
Case :	Collector

September 2012

Information furnished is believed to be accurate and reliable. However, Comset Semiconductors assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may results from its use. Data are subject to change without notice. Comset Semiconductors makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Comset Semiconductors assume any liability arising out of the application or use of any product and specifically disclaims any and all liability, including without limitation consequential or incidental damages. Comset Semiconductors' products are not authorized for use as critical components in life support devices or systems.