

Data Sheet

For Automotive Block Type EMIFIL® (LC Combined) for Automotive


BNX01*H Series

Dimensions





■ Insertion Loss Characteristics (Main Items)



■ Packaging

Code	Packaging	Minimum Quantity
-	Вох	150

■ Rated Value

Part Number	Rated Voltage	Withstand Voltage	Rated Current	Insulation Resistance(min.)	Insertion Loss
BNX012H01	50Vdc	125Vdc	15A	500M ohm	1MHz to 1GHz:40dB min. (20 to 25 degrees C line impedance=50 ohm)

Operating Temperature Range: -55°C to +125°C

In operating temperatures exceeding +85°C, derating of current is necessary.

Continued on the following page. |

This data sheet is applied for Block Type EMIFIL® used for Automotive Electronics equipment for your design.

⚠ Note:

- 1. This datasheet is downloaded from the website of Murata Manufacturing co., Itd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications. Therefore, please approve our product specifications or transact the approval sheet for product specifications before ordering.


Data Sheet

Continued from the preceding page.

Derating of Rated current

Rating

In operating temperatures exceeding +85°C, derating of current is necessary for BNX012H series. Please apply the derating curve shown in chart according to the operating temperature.



Power Supply BNX Circuit (BNX Input) (BNX Output) Power Supply + Bias СВ Load Circuit + Bias В Power Supply Ground PSG CG Load Circuit Ground Power Supply - Bias CB Load Circuit - Bias В PSG CG Power Supply Ground Load Circuit Ground

Connecting ± Power Line

In case of using ± power line, please connect to each terminal as shown.

■ ①Caution (Rating)

- 1. Do not use products beyond the rated current and rated voltage as this may create excessive heat and deteriorate the insulation resistance.
- 2. Be sure to provide an appropriate fail-safe function on your product to prevent a second damage that may be caused by the abnormal function or the failure our product.

This data sheet is applied for Block Type EMIFIL® used for Automotive Electronics equipment for your design.

♠ Note:

- 1. This datasheet is downloaded from the website of Murata Manufacturing co., ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications. Therefore, please approve our product specifications or transact the approval sheet for product specifications before ordering.