


FREQUENCY MIXERS

Designer's Kit K1-MCA1+

MINI-CIRCUITS DESIGNER'S KITS
SPEED UP
 THE SOLUTION!



300 to 12000 MHz

MCA1+ Features

- Very wide bandwidth
- Large selection of models, LO level 4, 7, 10, 13, 17
- Low conversion loss, 6 dB
- High L-R isolation to 40 dB typ.
- Rugged LTCC construction
- Low profile, 0.08"
- Low cost



All models are
RoHS compliant

only \$99⁹⁵ ea. kit (10 models, 5 of each, 50 total)

Kit K1-MCA1+ Electrical specifications of each model

Model	LO Level (dBm)	Frequency (MHz)		Conversion Loss (dB)	RF In @1 dB Compr. (dBm)	IP3 (dBm) (dB)	LO-RF Isolation (dB)	LO-IF Isolation
		LO/RF	IF					
MCA1-85L+	4.0	2800-8500	DC-1200	6.0	0.0	11	35	38
MCA1-12GL+	4.0	3800-12000	DC-1500	6.5	1.0	9	38	40
MCA1-24+	7.0	300-2400	DC-700	6.1	1.0	10	40	25
MCA1-42+	7.0	1000-4200	DC-1500	6.1	1.0	10	35	20
MCA1-60+	7.0	1600-6000	DC-2000	6.3	1.0	9	32	17
MCA1-24LH+	10.0	300-2400	DC-700	6.5	5.0	13	40	22
MCA1-60LH+	10.0	1700-6000	DC-2000	6.4	5.0	13	35	21
MCA1-42MH+	13.0	1000-4200	DC-1500	6.2	9.0	16	32	20
MCA1-80H+	17.0	5000-8000	DC-1250	6.3	14.0	24	35	35
MCA1-113H+	17.0	3800-11000	DC-1800	6.7	14.0	23	35	32

Protected under U.S. Patent 7,027,795



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 For quick access to product information see MINI-CIRCUITS CATALOG & WEB SITE

RF/IF & MICROWAVE COMPONENTS

REV. OR
M108654
K1-MCA1