



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089

NTE1502 Integrated Circuit 5-Step LED Driver Circuit for Linear Response

Description:

The NTE1502 is an integrated circuit in a 9-Lead SIP type package designed for driving 5-LED bar graphs or dot displays so that the LEDs may light linearly for input signal. Brightness of the LEDs can be controlled by using the output current adjustment pin provided.

Features:

- 5-LED Bar Graph or Dot Display Drive
- Linear Response with Respect to Input
- Brightness Externally Adjustable
- High Output Current, Suitable for Green LED Drive
- Lamp ON/OFF Hysteresis, No Flickering by Noise

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Supply Voltage, V_{CC}	-0.5V to +18V
Circuit Voltage, V_{8-5}	-0.5V to +16V
Load Current Set Input Voltage, V_{7-5}	+16V
Output Voltage (Note 1), V_O	-0.5V to +16V
Supply Current (Note 1), I_{CC}	18mA
Load Current Set Input Current (Note 2), I_7	5mA
Output Current (Note 1), I_O	20mA
Power Dissipation ($T_A = +75^\circ\text{C}$), P_D	550mW
Operating Ambient Temperature Range, T_{opr}	-20° to $+75^\circ\text{C}$
Storage Temperature Range, T_{stg}	-55° to $+150^\circ\text{C}$

Note 1. Output Pin1, Pin2, Pin3, Pin4, and Pin6.

Note 2. I_7 which can be set $I_O = 20\text{mA}$ is assumed to be the absolute rated value.

Electrical Characteristics: ($T_A = +25^\circ\text{C}$, $V_{CC} = 16\text{V}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Input Voltage (LED ON) LED 1	$V_{I(ON)1}$		1.63	1.83	2.00	V
LED 2	$V_{I(ON)2}$		2.20	2.43	2.64	V
LED 3	$V_{I(ON)3}$		2.80	3.03	3.27	V
LED 4	$V_{I(ON)4}$		3.38	3.64	3.88	V
LED 5	$V_{I(ON)5}$		3.92	4.14	4.37	V

Electrical Characteristics (Cont'd): ($T_A = +25^\circ\text{C}$, $V_{CC} = 16\text{V}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit		
Load Current Pin6	I_6	$V_O = 1.2\text{V}$, $I_7 = 4.25\text{mA}$	13	16	–	mA		
		Pin1 to Pin4	I_1 to I_4	$V_O = 2.5\text{V}$, $I_7 = 4.25\text{mA}$	13	16	–	mA
		Pin1 to Pin4, Pin6	I_1 to I_4 , I_6	$V_O = 16\text{V}$, $I_7 = 4.25\text{mA}$	–	16	19	mA
Input Current	I_8	$V_{8-5} = 8.5\text{V}$	–	–	50	μA		
		$V_{8-5} = 16\text{V}$	–	–	5	mA		
Supply Current	I_9	$V_{8-5} = 16\text{V}$	–	–	18	mA		
Output Pin Leakage Current	I_1 to I_4 , I_6	$V_O = 16\text{V}$	–	–	15	μA		

Pin Connection Diagram
(Front View)

