

# SILICON NPN RF POWER TRANSISTOR

**DESCRIPTION:**

The **ASI MRF260** is Designed for VHF Large Signal Power Amplifier Applications.

**MAXIMUM RATINGS**

<b>I<sub>C</sub></b>	1.0 A (CONT)
<b>V<sub>CE</sub></b>	18 V
<b>P<sub>DISS</sub></b>	12 W @ T <sub>C</sub> = 25 °C
<b>T<sub>J</sub></b>	-65 °C to +150 °C
<b>T<sub>STG</sub></b>	-65 °C to +150 °C
<b>θ<sub>JC</sub></b>	14.6 °C/W

**PACKAGE STYLE TO-220**

	DIMENSIONS			
	mm		inches	
	min	max	min	max
A	10	10.4	0.393	0.409
B	15.2	15.9	0.598	0.626
C	12.7	13.7	0.500	0.539
D	6.2	6.6	0.244	0.260
E	4.4	4.6	0.173	0.181
F	3.5	5.5	0.137	0.216
G	2.65	2.95	0.104	0.116
H	17.6 typ.		0.692 typ.	
L	1.14	1.7	0.044	0.067
M	3.75	3.85	0.147	0.151
N	1.23	1.32	0.048	0.051
P	0.41	0.64	0.016	0.025
R	2.4	2.72	0.094	0.107
S	4.95	5.15	0.194	0.203
T	2.4	2.7	0.094	0.106
U	0.61	0.94	0.024	0.037

1 = BASE    2 = EMITTER    3 =  
COLLECTOR    MOUNTING TAB = EMITTER

**CHARACTERISTICS**    T<sub>C</sub> = 25 °C

SYMBOL	TEST CONDITIONS	MINIMUM	TYPICAL	MAXIMUM	UNITS
<b>BV<sub>CEO</sub></b>	I <sub>C</sub> = 10 mA	18			V
<b>BV<sub>CES</sub></b>	I <sub>C</sub> = 5.0 mA	36			V
<b>I<sub>CB0</sub></b>	V <sub>CE</sub> = 15 V			0.25	mA
<b>I<sub>EB0</sub></b>	V <sub>EB</sub> = 4.0 V			1.0	mA
<b>h<sub>FE</sub></b>	V <sub>CE</sub> = 5.0 V    I <sub>C</sub> = 250 mA	5.0			---
<b>C<sub>ob</sub></b>	V <sub>CB</sub> = 15 V    f = 1.0 MHz			20	pF
<b>G<sub>PE</sub></b>	V <sub>CC</sub> = 12.5 V    P <sub>out</sub> = 5.0 W    f = 175 MHz	10	11		dB
<b>η</b>		55			%