



No.4287A

2SK2045

N-Channel Silicon MOSFET

Ultrahigh-Speed
Switching Applications**Features**

- Low ON resistance.
- Ultrahigh-speed switching.
- High-speed diode built in ($t_{tr}=140\text{ns}$).
- Micaless package facilitating easy mounting.



Absolute Maximum Ratings at $T_a=25^\circ\text{C}$

			unit
Drain-to-Source Voltage	V_{DSS}	600	V
Gate-to-Source Voltage	V_{GSS}	± 30	V
Drain Current(DC)	I_D	5.5	A
Drain Current(Pulse)	I_{DP}	22	A
Allowable Power Dissipation	P_D	2.0	W
		$T_c=25^\circ\text{C}$	
Channel Temperature	T_{ch}	35	W
Storage Temperature	T_{stg}	150	$^\circ\text{C}$
		-55 to +150	$^\circ\text{C}$

Electrical Characteristics at $T_a=25^\circ\text{C}$


			min	typ	max	unit
D-S Breakdown Voltage	$V_{(BR)DSS}$	$I_D=10\text{mA}, V_{GS}=0$	600			V
Zero-Gate Voltage	I_{DSS}	$V_{DS}=480\text{V}, V_{GS}=0$			1.0	mA
Drain Current						
Gate-to-Source Leakage Current	I_{GSS}	$V_{GS}=\pm 30\text{V}, V_{DS}=0$			± 100	nA
Cutoff Voltage	$V_{GS(\text{off})}$	$V_{DS}=10\text{V}, I_D=1\text{mA}$	2.0		3.0	V
Forward Transfer Admittance	$ Y_{fs} $	$V_{DS}=10\text{V}, I_D=3\text{A}$	2.3	4.5		S
Static Drain-to-Source	$R_{DS(on)}$	$I_D=3\text{A}, V_{GS}=10\text{V}$		1.1	1.5	Ω
ON-State Resistance						
Input Capacitance	C_{iss}	$V_{DS}=20\text{V}, f=1\text{MHz}$	1100			pF
Output Capacitance	C_{oss}	$V_{DS}=20\text{V}, f=1\text{MHz}$	150			pF
Reverse Transfer Capacitance	C_{rss}	$V_{DS}=20\text{V}, f=1\text{MHz}$	45			pF
Turn-ON Delay Time	$t_{d(on)}$	See specified Test Circuit.	18			ns
Rise Time	t_r	"	25			ns
Turn-OFF Delay Time	$t_{d(off)}$	"	240			ns
Fall Time	t_f	"	60			ns
Diode Forward Voltage	V_{SD}	$I_S=5.5\text{A}, V_{GS}=0$			1.5	V
Diode Reverse Recovery Time	t_{rr}	$I_S=5.5\text{A}, di/dt=100\text{A}/\mu\text{s}$	140			ns


(Note) Be careful in handling the 2SK2045 because it has no protection diode between gate and source.

Switching Time Test Circuit**Package Dimensions 2078B**
(unit : mm)

SANYO : TO-220FI(LS)

SANYO Electric Co., Ltd. Semiconductor Business Headquarters
TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110 JAPAN





- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use;
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of July, 1997. Specifications and information herein are subject to change without notice.