Ordering number: ENN8387



SANYO Semiconductors DATA SHEET

LA8151V — Monolithic Linear IC Downconverter IC for Digital CATV

Overview

The LA8151V is a downconverter IC for digital CATV. It accepts RF input frequencies from 50 to 280 MHz and supports the DOCSIS (USA) and Euro-DOCSIS (Europe) standards.

Features

- RF Attenuator.
- RF Mixer.
- Driver for SAW filter.
- IF AGC amplifier.
- IF Driver amplifier for ADC.

Specifications

Maximum Ratings at $Ta = 25^{\circ}C$

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	V _{CC} max	Pin 5, 10, 14, 15	6.0	V
Circuit voltages	V max	Pin 6	V _{CC}	V
Circuit current	I _{8,9}	Pin 8, 9 sink current	2	mA
Allowable power dissipation	Pd max	Ta≤70 °C	510*	mW
Operating temperature range	Topr		-20 to 70	°C
Storage temperature range	Tstg		-55 to 150	°C

^{*} On the board (114.3×76.1×1.6mm)

Operating Conditions at $Ta = 25^{\circ}C$

Parameter	Symbol	Conditions	Ratings	Unit
Recommended supply voltage	V _{CC}	Pin 5, 10, 14, 15	5.0	V
Operating supply voltage range	V _{CC op}	Pin 5, 10, 14, 15	4.5 to 5.5	V

- Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.
- SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO products described or contained herein.


AC Characteristics at Ta = 25°C, $V_{CC} = 5.0V$

Parameter	Symbol	Pin No.	0 177	Ratings			11.7
			Conditions	min	typ	max	Unit
Circuit current	I _{total}	5, 10, 14, 15	No Signal	55	65	78	mA
RF input frequency range*1	f(RF)	16, 17	Fc = -3dB	50		280	MHz
RF AGC range*1	GR1	19, 20	V6 = 0.5 to 2.5V	30	36		dB
Mixer conversion gain*1	CG1	19/16, 17 20/16, 17	V6 = 2.5V	21	24	27	dB
Mixer inter modulation 1*1	IM3 1	19/16, 17 20/16, 17	Input = $70dB\mu V$ V6 = $2.5V$	50	55		dB
IF input frequency range*2	f(IF)	2, 3	Fc = -3dB	30		100	MHz
IF amplifier gain *2	G _(AGC)	8/2, 3 9/2, 3	V6 = 2.5V	34	38	42	dB
IF inter modulation 2*2	IM3 2	8/2, 3 9/2, 3	Output = 104dBμV @2tone each	45	50		dB
IF AGC range *2	GR2	8, 9	IF Output Level < ±1dB	6	8		dB
IF output level*2	VO _(IF) 1	8	Single output		1.0		Vp-p
IF output level*2	Vo _(IF) 2	9	Single output		1.0		Vp-p

^{*1} Measurement circuit 1


Package Dimensions

unit: mm 3179C




^{*2} Measurement circuit 2

Pin Assignment




Block Diagram




Pin Description (unit: Ω) Pin Number Equivalent circuit Description GND AGC Amp Input 2 3 Bias 2 3 OMP05096 GND 4 5 V_{CC} 6 AGC Control VCC6 OMP05097 7 GND 8 Post Amp Outputs Vcc 30 30 OMP05098 10 V_{CC}

GND


Continued on next page.




Measurement Circuit 1



Measurement Circuit 2



Application Circuit



- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, of otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of September, 2005. Specifications and information herein are subject to change without notice.