



Bridge Rectifiers, Fast Recovery

(Continued)

I_O (AMPS)	10		25	35
@ T_A (°C)				
@ T_C (°C)	100	60	60	60
I_{FSM} (AMPS)	150	300	350	400
CASE				
V_{RRM} (VOLTS)				
100	CBR10F-J010	CBR10F-010P	CBR25F-010P	CBR35F-010P
200	CBR10F-J020	CBR10F-020P	CBR25F-020P	CBR35F-020P
400	CBR10F-J040	CBR10F-040P	CBR25F-040P	CBR35F-040P
600	CBR10F-J060	CBR10F-060P	CBR25F-060P	CBR35F-060P
800	CBR10F-J080			
1000	CBR10F-J100			

V_F MAX @ I_F	1.3V @ 5.0A	1.3V @ 5.0A	1.3V @ 12.5A	1.3V @ 17.5A
I_R MAX @ V_{RRM}	10 μ A	10 μ A	10 μ A	10 μ A
t_{rr} (100V thru 400V)	200ns	200ns	200ns	200ns
t_{rr} (600V thru 800V)	300ns	300ns	300ns	300ns
t_{rr} (1000V)	500ns			