

SERIES PROGRAMMABLE DC/DC CONVERTER



Power Solutions POWER ELECTRONICS DIVISION

POWER: 6 Amp

Parrallelable Boost Modules

SIZE: 2.00" x 0.60"

www.cdtechno.com click on Power Electronics

OBSOLETE PRODUCT DATA SHEET

Contact Factory for Replacement Model


FEATURES

- Small SIP Design
- Parallelable Boost SIP
 One stocking part meets a variety of loads
- Programmable Control SIP
 Control/Boost Pair extremely configurable
- Fast Transient Response No need for large external capacitors Extremely small footprint
- Low Component Count Low cost, high reliability
- Staked Pins
 Wave solderable
- Integrated Input Filter
 Low input ripple

APPLICATION NOTE

 DCAN-34 - 6-PAK Demo Board Downloadable from our website cdpowerelectronics.com The 6-PAKTM is a modular system of control and boost SIPs. Each 6A control SIP can also drive up to 8 additional 6A boost SIPs in parallel, for a total of 54A. Each SIP accepts a regulated 5V input (\pm 10%) and provides 2.5V to 3.6Vdc output. The circuit is optimized for high efficiency and fast load transient response needed by telecom, DSP and microprocessor applications.

Advanced thermal design, monolithic power circuitry and synchronous rectification result in outstanding performance and value. With integrated input filter and output capacitors, the 6-PAK system makes a complete power supply which requires no external components over the specified operating range. Pins are staked for wave solderability.



Electrical Specifications

Unless otherwise specified, operating conditions are as follows: $V_0 = 3.3V$, $T_A = 25^{\circ}C$, $C_{in} = 100 \mu F$

Parameter		Conditions	Min	Тур	Max	Units
Input						
Input Voltage	Vin		4.5	5.0	5.5	VDC
Input Current Ripple		$V_{\text{in}} = 4.5 V$ to 5.5V, $I_{\text{o}} = 6 A$			400	mА _{RMS}
Required Capacitance	Cin	Note 1	0	100		μF
Output						
Output Voltage	Vo	Nominal	3.25	3.3	3.35	VDC
Output Program Range		Note 2	2.5		3.6	VDC
Output Current	lo	$T_A = 60^{\circ}C$	0		6	Amps
Output Ripple		20Mhz BW		50	75	mVp-p
Output Rise Time	Tr	$V_{in} = 5V$, $I_o = 6A$ Resistive, $C_o = 0$		430	500	μS
Output Start-Up Time	Tr	$V_{in} = 5v$, $I_0 = 6A$ Resistive, $C_0 = 5000 \mu F$		3.0	4.0	mS
Output Capacitance Range Co			0		5000	μF
Line Regulation		l₀ = 6A		<u>+</u> 0.2	<u>+</u> 0.5	%
•		I₀ min - I₀ max, Vin = 4.5-5.5V		<u>+</u> 0.8	<u>+</u> 1.2	%
Temperature Coefficient $T_A = -40^{\circ}C$ to $+60^{\circ}C$		Vin = 5V, Io = 6A			<u>+</u> 0.01	%/°C
Combined Variation		V _{in} min-max &/or I₀ min-max T _A = -40°C to +60°C			<u>+</u> 2	%
Protection		Note 3				
General						
Switching Frequency				800		kHz
Dynamic Response						
$\Delta I_0/\Delta t = 1A/10 \mu sec$, V _i = 5.0V, T _A = 25°C						
Load Change from $I_0 = 0$	0% to lo = 100%					
Peak Deviation				20	30	mV
Settling time (V_0 <10% Peak Deviation)				130	200	μsec
Load change from $I_0 = 100\%$ to $I_0 = 0\%$ Peak Deviation				20	35	mV
Settling time (Vo<10% Peak Deviation)				200	300	μsec
Temperature						
Operating Temperature			-40		+60	°C
Storage Temperature			-40		+125	°C

<u>Notes</u>

- 1. Input source<3" from 6-PAK[™], load transient <3A per SIP. 100μF low ESR capacitor for load transients >3A per SIP.
- 2. Optional programming 2.5V 3.6V. See Table.
- 3. The unit is protected against short circuit on the output for durations not exceeding 10 seconds and a repetition rate of less than 5%.

Programming


The 6-PAK[™] is programmed through the Control SIP. All connected Power Boosters follow the Control SIP programming. To program the 6-PAK[™] for V_{out}<3.3, connect a resistor across the TRIM and V_opins. For V_{out}>3.3, resistor is connected across TRIM and GND.

Vout	Resistor Value	Vout	Resistor Value
2.5	196Ω	3.1	1.37k
2.6	255Ω	3.2	2.80k
2.7	332Ω	3.3	Open
2.8	442Ω	3.4	2.32k
2.9	604Ω	3.5	1.00k
3.0	866Ω	3.6	649Ω

ı


Transient Response

Operating conditions are as follows: Vin=5V, Vo=3.3V, Load change from Io=0% to Io=100%, TA=25°C, Cin=100 μ F, Co=0.




Tel: DOM: THE SHO

.



NOTE: The ambient temperature is as measured at approx. 1/4" away on the back side of the unit, with the probe end at approx. center (vertical & horizontal). For thermal performance, the unit was mounted on a 4"x4" PCB (with ground plane) & enclosed in a box so that it operates in a controlled environment.

Mechanical Outline



Pin Out

Pin	Function	Description		
1	Vo	Output Voltage		
2	Vo	Output Voltage		
3	TRIM	Output Adjust*		
4	GND	Ground		
5	INTI	InterModule 1		
6	Gnd	Ground		
7	INT2	InterModule 2		
8	Vi	5V Input Voltage		
9	Vi	5V Input Voltage		

* not connected on Boosters

System Interconnection Guidelines

- 1. Each SIP must have input, ground and output pins sunk into common input ground and output planes in the host PC board.
- 2. Two additional common signal traces are required to interconnect INT1 and INT2 pins. These traces must be a least 0.06" wide and make a straight connection among the modules.
- Power Booster SIP must be adjacent to the Control SIP located in the center of the layout, as shown in the Typical Example figure. Recommended distance between SIP pin centers is 0.5".
- A 300 LFM air flow is required in direction from Pin 9 to Pin 1, to draw rated power from booster configuration. Each application using boosters should be evaluated for thermal performance.

Standard Options are shown, consult factory for other available options.

C&D Technologies (Power Electronics) Ltd. Shannon, Co. Clare, Ireland Tel: +353.61.474.133 Fax:+353.61.474.141 Power Electronics Division, United States3400 E Britannia Drive, Tucson, Arizona 85706Tel: 800.547.2537Fax: 520.770.9369

C&D Technologies, (NCL) Milton Keynes MK14 5BU UK Tel: +44 (0)1908 615232 Fax: +44 (0)1908 617545

Any data, prices, descriptions or specifications presented herein are subject to revision by C&D Technologies, Inc. without notice. While such information is believed to be accurate as indicated herein, C&D Technologies, Inc. makes no warranty and hereby disclaims all warranties, express or implied, with regard to the accuracy or completeness of such information. Further, because the product(s) featured herein may be used under conditions beyond its control, C&D Technologies, Inc. hereby disclaims all warranties, either express or implied, concerning the fitness or suitability of such product(s) for any particular use or in any specific application or arising from any course of dealing or usage of trade. The user is solely responsible for determining the suitability of the product(s) featured herein for user's intended purpose and in user's specific application. C&D Technologies, Inc. does not warrant or recommend that any of its products be used in any life support or aviation or aerospace applications.