

DBF10

Silicon Diffused Junction Type

1.0A Single-Phase Bridge Rectifier


Features

- · Plastic molded structure.
- \cdot Peak reverse voltage: V_{RM} =100 to 600V.
- · Average rectified current:I_O=1.0A.

Package Dimensions

unit:mm

1210




Specifications


Absolute Maximum Ratings at Ta = 25°C


Parameter	Symbol	Conditions	DBF10B	DBF10C	DBF10E	DBF10G	Unit
Peak Reverse Voltage	V _{RM}		100	200	400	600	V
Average Rectified Current	IO	50Hz sine wave, resistive load, mounted on PCB	\rightarrow	\rightarrow	\rightarrow	1.0	Α
Surge Forward Current	IFSM	50Hz sine wave, nonrepetitive, 1cycle peak value	\rightarrow	\rightarrow	\rightarrow	30	Α
Junction Temperature	Tj		\rightarrow	\rightarrow	\rightarrow	150	°C
Storage Temperature	Tstg		\rightarrow	\rightarrow	\rightarrow	-40 to +150	°C

Electrical Characteristics at Ta = 25°C

Parameter	Symbol	Conditions		Unit		
			min	typ	max	
Forward Voltage	٧ _F	I _F =0.5A			1.05	V
Reverse Current	I _R	V _R =V _{RM}			10	μΑ
Thermal Resistance	θјі	Junction-lead			16	°C/W
	θја	Junction-ambient			62	°C/W







- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
 - ② Not impose any responsibilty for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of May, 1998. Specifications and information herein are subject to change without notice.