

# Bipolar Power Transistors

## Darlington Power Transistors (Continued)

Type No.	I <sub>C</sub> A	V <sub>CEO</sub> V		h <sub>FE</sub>		P <sub>T</sub> W	JEDEC Package
				I <sub>C</sub> A	V <sub>CE</sub> V		
<b>GE10015 FAMILY (n-p-n)</b>		<b>Devices have Integral Base Speed-up Diode</b>					
GE10015	50	400	25 min.	20	5	250	TO-204AE/ TO-3
GE10016	50	500	25 min.	20	5	250	
GE10020	60	200	75 min.	15	5	250	
GE10021	60	250	75 min.	15	5	250	
GE10022	40	350	50 min.	10	5	250	
GE10023	40	400	50 min.	10	5	250	
<b>RCA8766 FAMILY (n-p-n)</b>							
RCA8766	10	350	100 min.	6	3	150	TO-204AA/ TO-3
RCA8766A	10	350	100 min.	4	3	150	
RCA8766B	10	400	100 min.	6	3	150	
RCA8766C	10	400	100 min.	4	3	150	
BUX37	15	400	20 min.	15	5	35	
RCA8766D	10	450	100 min.	6	3	150	
RCA8766E	10	450	100 min.	4	3	150	
<b>RCA9202, RCA9203 (n-p-n)</b>							
RCA9202A	4	300	750 min.	2	3	65	TO-220AB Plastic Package
RCA9202B	4	350	750 min.	2	3	65	
RCA9202C	4	400	750 min.	2	3	65	
RCA9203A	4	250	500 min.	2	3	50	
RCA9203B	4	300	500 min.	2	3	50	
<b>RCA9228 (n-p-n)</b>		<b>Complementary to RCA9229 Family</b>					
RCA9228A	50	60	2000 min.	25	3	300	TO-204AE/ TO-3
RCA9228B	50	80	2000 min.	25	3	300	
RCA9228C	50	100	2000 min.	25	3	300	
RCA9228D	50	120	2000 min.	25	3	300	
<b>RCA9229 (p-n-p)</b>		<b>Complementary to RCA9228 Family</b>					
RCA9229A	-50	-60	2000 min.	-25	-3	300	TO-204AE/ TO-3
RCA9229B	-50	-80	2000 min.	-25	-3	300	
RCA9229C	-50	-100	2000 min.	-25	-3	300	
RCA9229D	-50	-120	2000 min.	-25	-3	300	
<b>TIP110 (n-p-n)</b>		<b>Complementary to TIP115 Family</b>					
TIP110	2	60	1000 min.	1	4	50	TO-220AB Plastic Package
TIP111	2	80	1000 min.	1	4	50	
TIP112	2	100	1000 min.	1	4	50	
<b>TIP115 (p-n-p)</b>		<b>Complementary to TIP110 Family</b>					
TIP115	-2	-60	1000 min.	-1	-4	50	TO-220AB Plastic Package
TIP116	-2	-80	1000 min.	-1	-4	50	
TIP117	-2	-100	1000 min.	-1	-4	50	