

SIGC06T60G

IGBT³ Chip

FEATURES:


- 600V Trench & Field Stop technology
- low V_{CE(sat)}
- low turn-off losses
- short tail current
- positive temperature coefficient
- easy paralleling

This chip is used for:

- power module
- discrete components

Applications:

- drives
- white goods
- resonant applications



Chip Type	V _{CE}	I _{Cn}	Die Size	Package	Ordering Code
SIGC06T60G	600V	10A	2.44 x 2.42 mm ²	sawn on foil	Q67050- A4344-A101

MECHANICAL PARAMETER:

MECHANICAE I ARAMETER.					
Raster size	2.44 x 2.42				
Emitter pad size	1.558 x 1.577	mm ²			
Gate pad size	0.361 x 0.513				
Area total / active	5.9 / 3.6	mm ²			
Thickness	70	μm			
Wafer size	150	mm			
Flat position	0	deg			
Max. possible chips per wafer	2485 pcs				
Passivation frontside	Photoimide				
Emitter metallization	3200 nm AlSiCu				
Collector metallization	1400 nm Ni Ag –system suitable for epoxy and soft solder die bonding				
Die bond	electrically conductive glue or solder				
Wire bond	Al, <500µm				
Reject ink dot size	Ø 0.65mm ; max 1.2mm				
Recommended storage environment	store in original container, in dry nitrogen, < 6 month at an ambient temperature of 23°C				



SIGC06T60G

MAXIMUM RATINGS:

Parameter	Symbol	Value	Unit	
Collector-emitter voltage, T_j = 25 °C	V _{CE}	600	V	
DC collector current, limited by T_{jmax}	I _C	1)	А	
Pulsed collector current, tp limited by Tjmax	I _{cpuls}	30	А	
Gate emitter voltage	V _{GE}	±20	V	
Operating junction and storage temperatur	T _j , T _{stg}	-40 +175	°C	
SC data, $V_{GE} = 15V$, $V_{CC} = 360V$	Tvj = 150°C	tp	6	μs
$G_{C} = G_{C} = G_{C$	Tvj = 25°C	ч [,]	8	P0

¹⁾ depending on thermal properties of assembly

STATIC CHARACTERISTICS (tested on chip), T_j =25 °C, unless otherwise specified

Parameter	Symbol	Conditions	Value			Unit
			min.	typ.	max.	
Collector-emitter breakdown voltage	V _{(BR)CES}	V_{GE} =0V , I _C = 2mA	600			
Collector-emitter saturation voltage	V _{CE(sat)}	V _{GE} =15V, I _C =10A	1.1	1.5	1.9	V
Gate-emitter threshold voltage	V _{GE(th)}	$I_C{=}150\mu A$, $V_{GE}{=}V_{CE}$	5.0	5.8	6.5	
Zero gate voltage collector current	I _{CES}	V_{CE} =600V , V_{GE} =0V			0.6	μA
Gate-emitter leakage current	I _{GES}	$V_{CE}=0V$, $V_{GE}=20V$			300	nA
Integrated gate resistor	R _{Gint}			none		Ω

ELECTRICAL CHARACTERISTICS (verified by design/characterization):

Parameter	Symbol	Conditions	Value			Unit
Falameter	Symbol		min.	typ.	max.	Unit
Input capacitance	Ciss	V _{CE} =25V,		551		pF
Output capacitance	Coss	$V_{GE}=0V$,		40		
Reverse transfer capacitance	Crss	f=1MHz		17		1

SWITCHING CHARACTERISTICS (verified by design/characterization), inductive load


Parameter	Symbol	Conditions	Value ²⁾			Unit
			min.	typ.	max.	
Turn-on delay time	t _{d(on)}	<i>T</i> _j =125°C		12		ns
Rise time	t _r	$V_{\rm CC} = 300 V$,		13		
Turn-off delay time	t _{d(off)}	I _C =10A, V _{GE} =-15/15V,		120		
Fall time	t _f	$R_{\rm G}$ = 27 Ω		130		

²⁾ values also influenced by parasitic L- and C- in measurement and package.

Edited by INFINEON Technologies AI PS DD CLS, L7521A, Edition 2, 27.01.2005



CHIP DRAWING:



Edited by INFINEON Technologies AI PS DD CLS, L7521A, Edition 2, 27.01.2005



SIGC06T60G

FURTHER ELECTRICAL CHARACTERISTICS:

This chip data sheet refers to the	
device data sheet	

DESCRIPTION:

AQL 0,65 for visual inspection according to failure catalog

Electrostatic Discharge Sensitive Device according to MIL-STD 883

Test-Normen Villach/Prüffeld

Published by Infineon Technologies AG, Bereich Kommunikation St.-Martin-Strasse 53, D-81541 München © Infineon Technologies AG 2004 All Rights Reserved.

Attention please!

The information herein is given to describe certain components and shall not be considered as warranted characteristics.

Terms of delivery and rights to technical change reserved.

We hereby disclaim any and all warranties, including but not limited to warranties of non-infringement, regarding circuits, descriptions and charts stated herein.

Infineon Technologies is an approved CECC manufacturer.

Information

For further information on technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies Office in Germany or our Infineon Technologies Representatives world-wide (see address list).

Warnings

Due to technical requirements components may contain dangerous substances. For information on the types in question please contact your nearest Infineon Technologies Office.

Infineon Technologies components may only be used in life-support devices or systems with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system, or to affect the safety or effectiveness of that device or system. Life support devices or systems are intended to be implanted in the human body, or to support and / or maintain and sustain and / or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.