SPECIFICATIONS FOR NICHIA CHIP TYPE WHITE LED MODEL : NESW021T

NICHIA CORPORATION

1.SPECIFICATIONS

((1)	Absolute	Maximum	Ratings
	. . ,	110501410	1viu//illuii	i itatiings

		(Ta=25°C)
Symbol	Absolute Maximum Rating	Unit
IF	15	mA
IFP	50	mA
Ir	85	mA
PD	60	mW
Topr	$-40 \sim +100$	°C
Tstg	$-40 \sim +100$	°C
Tsld	Reflow Soldering : 260°C	for 10sec.
	Hand Soldering : 350°C	for 3sec.
	IF IFP IR PD Topr Tstg	IF 15 IFP 50 IR 85 PD 60 Topr -40 ~ +100 Tstg -40 ~ +100 Tsld Reflow Soldering : 260°C

IFP Conditions : Pulse Width ≤ 10 msec. and Duty $\leq 1/10$

(2) Initial Electrical/Optical Characteristics

Item		Symbol	Condition	Тур.	Max.	Unit
Forward Voltage		VF	IF=10[mA]	(3.6)	4.0	V
Luminous Intensity		Iv	IF=10[mA]	(600)	-	mcd
Cl * X		-	IF=10[mA]	0.31	-	-
Chromaticity Coordinate	у	-	IF=10[mA]	0.32	-	-

* Please refer to CIE 1931 chromaticity diagram.

(3) Ranking					Γ)	[a=25°C)
	Item		Symbol	Condition	Min.	Max.	Unit
		Rank T	Iv	IF=10[mA]	720	1000	mcd
	Luminous Intensity	Rank S	Iv	IF=10[mA]	500	720	mcd
		Rank R	Iv	IF=10[mA]	360	500	mcd

* Luminous Intensity Measurement allowance is $\pm 10\%$.

Color Ranks

		Rank a0						
Х	0.280	0.280 0.264 0.283 0.296						
у	0.248	0.267	0.305	0.276				
		Rank b2						
х	0.296	0.287	0.330	0.330				
у	0.276	0.295	0.339	0.318				

(IF=1	0mA	Ta=	25°	C
(11) 1	UIII I	, 1 a	25	\mathcal{I}

(Ta=25°C)

(11 101111, 10 20 0)							
	Rank b1						
0.287	0.283	0.330	0.330				
0.295	0.305	0.360	0.339				
	Rank c0						
0.330	0.330	0.361	0.356				
0.318	0.360	0.385	0.351				
	0.295	0.287 0.283 0.295 0.305 Ran 0.330 0.330	0.287 0.283 0.330 0.295 0.305 0.360 Rank c0 0.330 0.330 0.361				

* Color Coordinates Measurement allowance is ± 0.01 .

* One delivery will include up to two consecutive color ranks and three luminous intensity ranks of the products. The quantity-ratio of the ranks is decided by Nichia.

2.INITIAL OPTICAL/ELECTRICAL CHARACTERISTICS Please refer to figure's page.

3.OUTLINE DIMENSIONS AND MATERIALS

Please refer to figure's page.

Material as follows ;

Package	:	Heat-Resistant Polymer
Encapsulating Resin	:	Epoxy Resin (with Diffused + Phosphor)
Electrodes	:	Ag Plating Copper Alloy

4.PACKAGING

• The LEDs are packed in cardboard boxes after taping.

Please refer to figure's page.

The label on the minimum packing unit shows ; Part Number, Lot Number, Ranking, Quantity

- \cdot In order to protect the LEDs from mechanical shock, we pack them in cardboard boxes for transportation.
- The LEDs may be damaged if the boxes are dropped or receive a strong impact against them, so precautions must be taken to prevent any damage.
- The boxes are not water resistant and therefore must be kept away from water and moisture.
- · When the LEDs are transported, we recommend that you use the same packing method as Nichia.

5.LOT NUMBER

The first six digits number shows lot number.

The lot number is composed of the following characters;

 $\bigcirc \Box \times \times \times \times \text{ - } \bigtriangleup \blacksquare$

- - Year (5 for 2005, 6 for 2006)
- \Box Month (1 for Jan., 9 for Sep., A for Oct., B for Nov.)
- $\times \times \times \times$ Nichia's Product Number
 - \triangle Ranking by Color Coordinates
 - Ranking by Luminous Intensity

6.RELIABILITY (1) TEST ITEMS AND RESULTS

	Standard			Number of
Test Item	Test Method	Test Conditions	Note	Damaged
Resistance to	JEITA ED-4701	Tsld=260°C, 10sec.	2 times	0/22
Soldering Heat	300 301	(Pre treatment 30°C,70%,168hrs.)		
(Reflow Soldering)				
Solderability	JEITA ED-4701	Tsld= $215 \pm 5^{\circ}$ C, 3sec.	1 time	0/22
(Reflow Soldering)	300 303	(using flux, Lead Solder)	over 95%	
Thermal Shock	JEITA ED-4701	$-40^{\circ}C \sim 100^{\circ}C$	100 cycles	0/100
	300 307	1min. (10sec.) 1min.		
		(Pre treatment 30°C,70%,168hrs.)		
Temperature Cycle	JEITA ED-4701	$-40^{\circ}\mathrm{C}\sim25^{\circ}\mathrm{C}\sim100^{\circ}\mathrm{C}\sim25^{\circ}\mathrm{C}$	100 cycles	0/100
	100 105	30min. 5min. 30min. 5min.		
Moisture Resistance Cyclic	JEITA ED-4701	$25^{\circ}\text{C} \sim 65^{\circ}\text{C} \sim -10^{\circ}\text{C}$	10 cycles	0/100
	200 203	90%RH 24hrs./1cycle		
High Temperature Storage	JEITA ED-4701	Ta=100°C	1000 hrs.	0/100
	200 201			
Temperature Humidity	JEITA ED-4701	Ta=60°C, RH=90%	1000 hrs.	0/100
Storage	100 103			
Low Temperature Storage	JEITA ED-4701	Ta=-40°C	1000 hrs.	0/100
	200 202			
Steady State Operating Life		Ta=25°C, IF=15mA	1000 hrs.	0/100
**				
Steady State Operating Life		Ta=85°C, IF=7.2mA	1000 hrs.	0/100
of High Temperature **				
Steady State Operating Life		60°C, RH=90%, IF=10mA	1000 hrs.	0/100
of High Humidity Heat **			1000 110.	0/100
Steady State Operating Life		Ta=-40°C, IF=10mA	1000 hrs.	0/100
of Low Temperature **			1000 110.	0,100
Permanence of Marking	JEITA ED-4701	Solvent : Isopropyl Alcohol	1 time	0/22
	500 501	Solvent Temperature : $20 \sim 25^{\circ}$ C	1 tillt	0/22
	200201	Dipping Time : 5 min.		
Vibration	JEITA ED-4701	200m/s^2 , 100 ~ 2000Hz (Sweep 4min.)	4 times	0/10
101000	400 403	48min., 3directions	i times	0/10
Drop	100 105	75cm	3 times	0/10
Electrostatic Discharge	JEITA ED-4701	R=1.5kΩ, C=100pF	3 times	0/10
Electrostatic Discharge				0/22
	300 304	Test Voltage=2kV	Negative/Positive	

(2) CRITERIA FOR JUDGING DAMAGE

			Criteria for Judgement	
Item	Symbol	Test Conditions	Min.	Max.
Forward Voltage	VF	IF=10mA	-	U.S.L.*)× 1.1
Luminous Intensity Condition 1	Iv	IF=10mA	L.S.L.**)× 0.7	-
Luminous Intensity Condition 2 **	Iv	IF=10mA	L.S.L.**)× 0.5	-

*) U.S.L. : Upper Standard Level

**) L.S.L.: Lower Standard Level

***** These test items are judged by the criteria of Luminous Intensity Condition 2.

7.CAUTIONS

The LEDs are devices which are materialized by combining Blue LEDs and special phosphors. Consequently, the color of the LEDs is changed a little by an operating current. Care should be taken after due consideration when using LEDs.

(1) Moisture Proof Package

• When moisture is absorbed into the SMT package it may vaporize and expand during soldering. There is a possibility that this can cause exfoliation of the contacts and damage to the optical characteristics of the LEDs. For this reason, the moisture proof package is used to keep moisture to a minimum in the package.

• The moisture proof package is made of an aluminum moisture proof bag with a zipper. A package of a moisture absorbent material (silica gel) is inserted into the aluminum moisture proof bag. The silica gel changes its color from blue to pink as it absorbs moisture.

(2) Storage

· Storage Conditions

Before opening the package :

The LEDs should be kept at 30°C or less and 90%RH or less. The LEDs should be used within a year. When storing the LEDs, moisture proof packaging with absorbent material (silica gel) is recommended.

After opening the package :

The LEDs should be kept at 30°C or less and 70%RH or less. The LEDs should be soldered within 168 hours (7days) after opening the package. If unused LEDs remain, they should be stored in moisture proof packages, such as sealed containers with packages of moisture absorbent material (silica gel). It is also recommended to return the LEDs to the original moisture proof bag again.

• If the moisture absorbent material (silica gel) has faded away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions.

Baking treatment : more than 24 hours at $65 \pm 5^{\circ}C$

- Nichia LED electrodes are silver plated copper alloy. The silver surface may be affected by environments which contain corrosive substances. Please avoid conditions which may cause the LED to corrode, tarnish or discolor. This corrosion or discoloration may cause difficulty during soldering operations. It is recommended that the User use the LEDs as soon as possible.
- Please avoid rapid transitions in ambient temperature, especially in high humidity environments where condensation can occur.

(3) Heat Generation

• Thermal design of the end product is of paramount importance. Please consider the heat generation of the LED when making the system design. The coefficient of temperature increase per input electric power is affected by the thermal resistance of the circuit board and density of LED placement on the board, as well as other components. It is necessary to avoid intense heat generation and operate within the maximum ratings given in this specification.

• The operating current should be decided after considering the ambient maximum temperature of LEDs.

(4) Soldering Conditions

The LEDs can be soldered in place using the reflow soldering method. Nichia cannot make a guarantee on the LEDs after they have been assembled using the dip soldering method.
Recommended soldering conditions

	Reflow Solderin	g	Hand S	oldering	
	Lead Solder	Lead-free Solder		U	
Pre-heat	120 ~ 150°C	180 ~ 200°C	Temperature	350°C Max.	
Pre-heat time	120 sec. Max.	120 sec. Max.	Soldering time	3 sec. Max.	
Peak temperature	240°C Max.	260°C Max.		(one time only)	
Soldering time	10 sec. Max.	10 sec. Max.			
Condition	refer to	refer to			
	Temperature - profile ①.	Temperature - profile ②.			
		(N ₂ reflow is recommended.)			

* After reflow soldering rapid cooling should be avoided.

[Temperature-profile (Surface of circuit board)]

Use the conditions shown to the under figure.

<① : Lead Solder>





[Recommended soldering pad design]

Use the following conditions shown in the figure.



• Occasionally there is a brightness decrease caused by the influence of heat or ambient atmosphere during air reflow. It is recommended that the User use the nitrogen reflow method.

- Repairing should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used. It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.
- \cdot Reflow soldering should not be done more than two times.
- \cdot When soldering, do not put stress on the LEDs during heating.
- · After soldering, do not warp the circuit board.

(5) Cleaning

- It is recommended that isopropyl alcohol be used as a solvent for cleaning the LEDs. When using other solvents, it should be confirmed beforehand whether the solvents will dissolve the package and the resin or not. Freon solvents should not be used to clean the LEDs because of worldwide regulations.
- Do not clean the LEDs by the ultrasonic. When it is absolutely necessary, the influence of ultrasonic cleaning on the LEDs depends on factors such as ultrasonic power and the assembled condition. Before cleaning, a pre-test should be done to confirm whether any damage to the LEDs will occur.

(6) Static Electricity

· Static electricity or surge voltage damages the LEDs.

- It is recommended that a wrist band or an anti-electrostatic glove be used when handling the LEDs.
- All devices, equipment and machinery must be properly grounded. It is recommended that precautions be taken against surge voltage to the equipment that mounts the LEDs.
- When inspecting the final products in which LEDs were assembled, it is recommended to check whether the assembled LEDs are damaged by static electricity or not. It is easy to find static-damaged LEDs by a light-on test or a VF test at a lower current (below 1mA is recommended).
- Damaged LEDs will show some unusual characteristics such as the forward voltage becomes lower, or the LEDs do not light at the low current.

Criteria : (VF > 2.0V at IF=0.5mA)

(7) Others

- \cdot The LED light output is strong enough to injure human eyes. Precautions must be taken to prevent looking directly at the LEDs with unaided eyes for more than a few seconds.
- Flashing lights have been known to cause discomfort in people; you can prevent this by taking precautions during use. Also, people should be cautious when using equipment that has had LEDs incorporated into it.
- The LEDs described in this brochure are intended to be used for ordinary electronic equipment (such as office equipment, communications equipment, measurement instruments and household appliances). Consult Nichia's sales staff in advance for information on the applications in which exceptional quality and reliability are required, particularly when the failure or malfunction of the LEDs may directly jeopardize life or health (such as for airplanes, aerospace, submersible repeaters, nuclear reactor control systems, automobiles, traffic control equipment, life support systems and safety devices).
- User shall not reverse engineer by disassembling or analysis of the LEDs without having prior written consent from Nichia. When defective LEDs are found, the User shall inform Nichia directly before disassembling or analysis.
- The formal specifications must be exchanged and signed by both parties before large volume purchase begins.
- The appearance and specifications of the product may be modified for improvement without notice.



* Color Coordinates Measurement allowance is ± 0.01 .



Nichia STSE-CC5074B <Cat.No.060530>



Nichia STSE-CC5074B <Cat.No.060530>



-10-

Nichia STSE-CC5074B <Cat.No.060530>



Nichia

