
PDP-3Q-525 0° POWER DIVIDERS / COMBINERS

50 to 1000 MHz / 3-Way / Low Insertion Loss / Wideband / Meri-Pac / Auto-Insertion-Ready



Model Number	Frequency Range, MHz	Freq. Perform., MHz	lsolation, dB,		Insertion Loss, dB,		Phase Balance,		Amplitude Balance, dB,			
											VSWR	
			Min.	Тур.	Max.	Тур.	Max.	Тур.	Max.	Тур.	Max.	Тур
PDP-3Q-525	50 - 1000	50 - 800	20	25	1.5	0.8	8°	3°	0.5	0.3	1.5:1	1.3:1
		800 - 1000	20	25	2.25	1.5	10°	5°	0.7	0.5	1.7:1	1.4:1



For further information contact MERRIMAC/41 Fairfield PI., West Caldwell, NJ, 07006 / 973-575-1300 / FAX 973-575-0531