T-11-2500A-D3-SSC • T-11-2500A-D3-SLC



Features

- InGaAs/ InP PIN Photodiode with transimpedance amplifier
- High sensitivity with Auto Gain Control (AGC)
- Differential ended output
- Single +3.3 V operation
- -40 to +85°C operating temperature

Packaging

• SC/ LC ROSA package

Application

- 2.5 Gbps SONET/ SDH receivers
- 2.5 Gbps ATM receiver

Absolute Maximum Ratings (T _c = 25°C)				DC Electrical Characteristics (T _c = 25°C)					
Parameter	Symbol	Value	Unit	Parameter	Symbol	Min	Тур	Max	Unit
Supply Voltage	V _{cc}	4.5	V	Power Supply	V _{cc}	3	3.3	3.6	V
Operating Temperature	T _{opr}	-40 to +85	°C	Differential Output Voltage	Vd	-	0.6	-	V
Storage Temperature	T _{stg}	-40 to +85	°C	Supply Current (no load)	I _{cc}	-	34	-	mA

AC Optical and Electrical Characteristics ($T_c = 25^{\circ}$ C)								
Parameter	Symbol	Min.	Тур	Max	Unit	Test Condition		
Detection Range		1100	1310	1650	nm	-		
Gain @ 10 MBps	C		77		1//m)//	h = 1210 pm		
Differential	G	-	27	-	V/IIIVV	λ = 1310 ΠΠ		
Bandwidth	D\\/	1600	1900	2000				
(to –3dB point)	DVV	1000	1800	2000	IVITIZ	_		
Saturation Power	P _{sat}	-3	0	-	dBm	$\lambda = 1310 \text{ nm}$		
Sensitivity	Sens	-	-21	-18	dBm	BER = 10 ⁻⁹ @ 2.5 Gbps		
Output Resistance	R _{out}	48	60	72	ohm	-		

Operating at V_{cc} = 3.3 V, T_c = 25 °C, λ = 1310 nm, 9/125 μm SM fiber

Connector Options					
Model	Package	Fiber	Connector		
T-11-2500A-D3-SSC	ROSA	-	SC		
T-11-2500A-D3-SLC	ROSA	-	LC		

T-11-2500A-D3-SSC • T-11-2500A-D3-SLC







Warnings

Handling Precautions: This device is susceptible to damage as a result of electrostatic discharge (ESD). A static free environment is highly recommended. Follow guidelines according to proper ESD procedures.

Legal Notice

IMPORTANT NOTICE!

All information contained in this document is subject to change without notice, at Luminent's sole and absolute discretion. Luminent warrants performance of its products to current specifications only in accordance with the company's standard one-year warranty; however, specifications designated as "preliminary" are given to describe components only, and Luminent expressly disclaims any and all warranties for said products, including express, implied, and statutory warranties, warranties of merchantability, fitness for a particular purpose, and non-infringement of proprietary rights. Please refer to the company's Terms and Conditions of Sale for further warranty information.

Luminent assumes no liability for applications assistance, customer product design, software performance, or infringement of patents, services, or intellectual property described herein. No license, either express or implied, is granted under any patent right, copyright, or intellectual property right, and Luminent makes no representations or warranties that the product(s) described herein are free from patent, copyright, or intellectual property rights. Products described in this document are NOT intended for use in implantation or other life support applications where malfunction may result in injury or death to persons. Luminent customers using or selling products for use in such applications do so at their own risk and agree to fully defend and indemnify Luminent for any damages resulting from such use or sale.

THE INFORMATION CONTAINED IN THIS DOCUMENT IS PROVIDED ON AN "AS IS" BASIS. Customer agrees that Luminent is not liable for any actual, consequential, exemplary, or other damages arising directly or indirectly from any use of the information contained in this document. Customer must contact Luminent to obtain the latest version of this publication to verify, before placing any order, that the information contained herein is current.

© Luminent, Inc. 2002 All rights reserved