
5 to 2000 MHz / 10 dB & 20 dB Models / Multi-Octave Units / Low Profile Surface Mount Package





PRINCIPAL SPECIFICATIONS							
Model Number	Frequency Range, MHz	Performance Bandwidth, MHz	¤ Coupling dB, Nom.	Frequency Sensitivity, dB, Max.	Directivity, dB, Min.	*Insertion Loss, dB, Max.	VSWR Max.
CBG-10B-375	5 - 750	5 - 750	10 ± 1.0	± 0.5	20	1.3	1.5:1
CBG-20B-375	5 - 750	5 - 750	20 ± 1.0	± 0.75	18	1.0	1.5:1
		10 - 400	20 ± 1.0	± 0.5	20	0.6	1.3:1
CBG-11B-1250	100 - 2000	100 - 2000	11 ± 1.0	± 0.5	15	1.5	1.7:1
		500 - 1000	11 ± 1.0	± 0.5	15	1.2	1.5:1
CBG-20B-1250	100 - 2000	100 - 2000	20 ± 1.0	± 0.5	15	1.5	1.7:1
		500 - 1000	20 ± 1.0	± 0.5	15	1.2	1.5:1
¤ (* Insertion Loss excludes Coupling Loss					

General Notes:

- 1. Directional couplers find applications in monitoring of incident and reflected power, sampling for control loops as well as signal injection devices in BITE systems.
- 2. These Directional Couplers are 3 port devices with one port internally terminated. They also may be used back-to-back as Dual Directional Couplers, or ordered with both coupled ports available, as Bi-Directional Couplers in the CRG-B series.
- 3. Optional performance characteristics for this series include frequencies up to 2.5 GHz, coupling from 5 to 30 dB, close tolerance coupling and more.

GENERAL SPECIFICATIONS

