
QED633 QED634





DESCRIPTION

The QED634 is a 940 nm GaAs / AlGaAs LED encapsulated in a clear untinted, plastic T-1 3/4 package.

1 OF 4

FEATURES

- λ= 940 nm
- Chip material =GaAs with AlGaAs window
- Package type: T-1 3/4 (5mm lens diameter)
- Matched Photosensor: QSD122/123/124
- Wide Emission Angle, 55°
- High Output Power
- Package material and color: Clear, untinted, plastic
- · Ideal for remote control applications



QED633 QED634

ABSOLUTE MAXIMUM RATINGS (T _A = 25°C unless otherwise specified)							
Parameter	Symbol	Rating	Unit				
Operating Temperature	T _{OPR}	-40 to +100	°C				
Storage Temperature	T _{STG}	-40 to +100	°C				
Soldering Temperature (Iron)(2,3,4)	T _{SOL-I}	240 for 5 sec	°C				
Soldering Temperature (Flow)(2,3)	T _{SOL-F}	260 for 10 sec	°C				
Continuous Forward Current	I _F	100	mA				
Reverse Voltage	V _R	5	V				
Power Dissipation ⁽¹⁾	P _D	200	mW				
Peak Forward Current	I _{FP}	1.5	A				

- 1. Derate power dissipation linearly 2.67 mW/°C above 25°C.
- 2. RMA flux is recommended.
- 3. Methanol or isopropyl alcohols are recommended as cleaning agents.
- 4. Soldering iron 1/16" (1.6mm) minimum from housing.
- 5. Pulse conditions; $tp = 100 \mu s$, T = 10 ms.

ELECTRICAL / OPTICAL CHARACTERISTICS (TA =25°C)										
PARAMETER	TEST CONDITIONS	DEVICE	SYMBOL	MIN	TYP	MAX	UNITS			
Peak Emission Wavelength	I _F = 20 mA	ALL	λ_{PE}	_	940	_	nm			
Spectral Bandwidth	I _F = 20 mA	ALL	_	50	_	nm				
Temp. Coefficient of λ_{PE}	I _F = 100 mA	ALL	TC_λ	_	0.2	_	nm/K			
Emission Angle	I _F = 100 mA	ALL	201/ ₂	_	55	_	Deg.			
Forward Voltage	$I_F = 100 \text{ mA}, \text{ tp} = 20 \text{ ms}$	ALL	V _F	_	_	1.6	V			
Temp. Coefficient of V _F	I _F = 100 mA	ALL	TC _V	_	-1.5	_	mV/K			
Reverse Current	V _R = 5 V	ALL	I _R	_	_	10	μA			
Radiant Intensity	I _F = 100 mA, tp = 20 ms	QED633	I _E	15	25	_	mW/sr			
		QED634		20	25	_				
Temp. Coefficient of I _E	I _F = 20 mA	ALL	TCı	_	-0.6	_	%/K			
Rise Time	I _E = 100 mA	ALL	t _r	_	1000	_	. ns			
Fall Time	1 _F = 100 Hi/t	ALL	t _f	_	1000	_				



QED633 QED634

TYPICAL PERFORMANCE CURVES TBD

Fig. 1 Normalized Radiant Intensity vs. Forward Current




Fig. 2 Forward Voltage Vs. Ambient Temperature




Fig. 3 Normalized Radiant Intensity vs. Wavelength




Fig. 4 Radiation Diagram





Fig. 5 Forward Current vs. Forward Voltage





QED633 QED634

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body,or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.